

NASA CR-159,279



NASA Contractor Report 159279

NASA-CR-159279  
19820025141

DOCUMENTATION OF PROGRAM COORDC  
TO GENERATE COORDINATE SYSTEM  
FOR 3-D CORNERS WITH OR WITHOUT  
FILLET USING BODY-FITTED CURVILINEAR  
COORDINATES-Part II

Dilip Kumar

SYSTEMS AND APPLIED SCIENCES CORPORATION  
Hampton, Virginia 23666

~~FOR EARLY DOMESTIC DISSEMINATION~~

~~Because of its significant early commercial potential, this information which has been developed under a U. S. Government contract is being disseminated within the United States in advance of general publication. This information may be duplicated and used by the recipient with the express limitation that it not be published. Release of this information to other domestic parties by the recipient shall be made subject to these limitations. Foreign release may be made only with prior NASA approval and appropriate export licenses. This legend shall be marked on any reproduction of this information in whole or in part.~~

DATE OF GENERAL RELEASE JUNE 1982.

NASA Contract NAS1-15604  
June 1980



National Aeronautics and  
Space Administration

Langley Research Center  
Hampton, Virginia 23665

LIBRARY COPY

JUL 11 1980

LANGLEY RESEARCH CENTER  
1001 W. MAIN  
HAMPTON, VIRGINIA



NF01088

## TABLE OF CONTENTS

	<u>Page</u>
Abstract . . . . .	i
List of Symbols . . . . .	ii
I. Numerical Generation of Body-Fitted Curvilinear Coordinate Systems . . . . .	1
A. Mathematics of Transformation . . . . .	2
B. Numerical Solution Technique. . . . .	6
C. Initial Guess and Boundary Point Specification. . . . .	9
D. x-Coordinate and Metric Coefficients. . . . .	9
E. Concluding Remarks. . . . .	11
II. Computer Program . . . . .	14
A. Listing of the Computer Program . . . . .	15
B. Job Control Cards . . . . .	29
C. Input Explanation . . . . .	29
D. Sample Input. . . . .	30
E. Sample Output . . . . .	34
III. Programmer/Analyst Section. . . . .	49
A. Main Program COORDC . . . . .	49
B. Subroutine CALCOR . . . . .	50
C. Subroutine IPRTC . . . . .	51
D. Subroutine IPLTC . . . . .	51
E. Block Diagram . . . . .	51

N80-74862 #

# ABSTRACT

The computer program COORDC generates a body-fitted curvilinear coordinate system for corner geometry with or without corner fillets. It is assumed that at any given  $\xi$ ,  $x$  remains constant; consequently the only variation is in  $y$  and  $z$ . It is also assumed that for all  $\xi$ 's in the physical plane the coordinate system in  $y$ - $z$  plane is similar. This enables solution of coordinate system for one particular  $\xi = 1$  ( $x$  for  $\xi = 1$  is arbitrarily chosen to be 0.0) and the solution for all other  $\xi$  plane can be easily specified once the coordinates in the physical plane on the line  $1 \leq \xi \leq \text{IMAX}$ ,  $\eta = 1$ ,  $\zeta = 1$  are specified.

### List of Symbols

IMAX	Maximum number of points in $\xi$ - direction
JMAX	Maximum number of points in $\eta$ - direction
KMAX	Maximum number of points in $\zeta$ - direction
J	Jacobian
P,Q,R	Inhomogeneous terms used for coordinate attraction
S,O,R	Successive-Over-Relaxation iteration
X,Y,Z	Physical Coordinates
$\alpha,\beta,\gamma$	Metric Coefficients
$\xi,\eta,\zeta$	Transformed Coordinates
$\Gamma_1,\Gamma_2,\Gamma_3,\Gamma_4$	Boundary contours in the physical plane
$\Gamma_1^*,\Gamma_2^*,\Gamma_3^*,\Gamma_4^*$	Boundary contours in the transformed plane
$\omega$	Acceleration parameter for Gauss-Seidel iteration

### Subscripts

$\xi,\eta,\zeta,x,y,z$	Denotes first partial differentiation
$\xi\xi,\eta\eta,xx,yy$ etc.	Denotes second partial differentiation
$\xi\eta,xy,xz$ etc.	Denotes cross partial differentiation

### Superscripts

(s)	Denotes the iteration number
-----	------------------------------

## I. Numerical Generation of Body-Fitted Curvilinear Coordinate Systems

The method for numerically generating boundary-fitted curvilinear coordinate systems is presented as applicable in a specialized 3-D corner with or without a fillet. The coordinate system is generated such that for a specified  $\xi$ ,  $x$  remains constant and for all  $\xi$ 's the solution in  $y$ - $z$  plane stays similar. This is particularly beneficial because for  $\xi = 1$  plane ( $x$  is chosen to be 0.0 for  $\xi = 1$ )  $y$ - $z$  solution can be obtained numerically by the 2-D formulation instead of 3-D formulation of the body-fitted curvilinear coordinate system. The coordinates for all other  $\xi$  planes can be easily obtained once the physical plane coordinates on the line  $\xi = 1$ ,  $IMAX$ ,  $\eta = 1$ ,  $\zeta = 1$  are specified. In the present problem it is assumed that for a given  $\xi$  plane, right boundary and upper boundary have  $z$  and  $y$  constant respectively. In addition, on the left wall and the bottom wall,  $z$  and  $y$  respectively equal zero some distance from the corner when fillet is present; in case of no fillet  $z$  and  $y$  on left and bottom wall respectively is equal to zero. The clustering of  $\eta$  and  $\zeta$  lines is specified by the point distribution on  $\eta = 1$  and  $\zeta = 1$  line.

Section A provides a brief discussion of the mathematical formulation and section B describes the numerical technique used to generate the coordinate system. Section C explains how the required initial guess is specified. Section D deals with handling of the  $x$ -coordinate and the metric coefficients.

## A. Mathematics of Transformation

Consider the transformation of a simply connected region  $R$ , into a rectangular region as shown in Figure 1. We require that  $\Gamma_1, \Gamma_2, \Gamma_3, \Gamma_4$  map into  $\Gamma_1^*, \Gamma_2^*, \Gamma_3^*, \Gamma_4^*$  respectively. For identification purposes, region  $D$  is referred to as the physical plane, and  $D^*$  as the transformed plane. In the physical plane it is assumed that  $x$  is constant for a specified  $\xi$ ,  $z$  is constant on  $\Gamma_3$  and  $y$  is constant on  $\Gamma_4$ . If for  $\xi = 1$ ,  $x = 0.0$  is assumed, then the transformation from  $x, y, z$  to  $\xi, \eta, \zeta$  is defined as follows,

$$\begin{bmatrix} \xi \\ \eta \\ \zeta \end{bmatrix} = \begin{bmatrix} \xi(x) \\ \eta(y, z) \\ \zeta(y, z) \end{bmatrix} \quad (1)$$

The above equation is solved only for  $\eta$  and  $\zeta$  since  $\xi$  is explicitly known. Assuming that an inverse transformation exists, then

$$\begin{bmatrix} y \\ z \end{bmatrix} = \begin{bmatrix} y(\eta, \zeta) \\ z(\eta, \zeta) \end{bmatrix} \quad (2)$$

where the jacobian  $J$  is as follows:

$$J = y_{\eta} z_{\zeta} - y_{\zeta} z_{\eta} \quad (3)$$

The generating elliptic system is chosen to be the inhomogeneous Laplace equation,

$$\eta_{yy} + \eta_{zz} = Q(\eta, \zeta) \quad (4a)$$

$$\zeta_{yy} + \zeta_{zz} = R(\eta, \zeta) \quad (4b)$$

with the boundary conditions as follows:

$$\text{on } \Gamma_1 \quad \begin{bmatrix} \eta \\ \zeta \end{bmatrix} = \begin{bmatrix} \eta_1(y,z) \\ \zeta_1 \end{bmatrix} \quad (5a)$$

$$\text{on } \Gamma_2 \quad \begin{bmatrix} \eta \\ \zeta \end{bmatrix} = \begin{bmatrix} \eta_2 \\ \zeta_2(y,z) \end{bmatrix} \quad (5b)$$

$$\text{on } \Gamma_3 \quad \begin{bmatrix} \eta \\ \zeta \end{bmatrix} = \begin{bmatrix} \eta_3(y,z) \\ \zeta_3 \end{bmatrix} \quad (5c)$$

$$\text{and on } \Gamma_4 \quad \begin{bmatrix} \eta \\ \zeta \end{bmatrix} = \begin{bmatrix} \eta_4 \\ \zeta_4(y,z) \end{bmatrix} \quad (5d)$$

where  $\zeta_1, \eta_2, \zeta_3, \eta_4$  are specified constants and  $\eta_1, \zeta_2, \eta_3, \zeta_4$  are specified functions.

The inhomogeneous terms  $Q$  and  $R$  are selected to control the spacing of  $\eta = \text{constant}$  and  $\zeta = \text{constant}$  lines in the physical plane; several forms for the inhomogeneous terms can be used. In the present case a special form of  $Q$  and  $R$  terms was used based on the point distribution on  $\eta = \eta_2$  and  $\zeta = \zeta_1$  line. (For convenience  $\eta_2 = \zeta_1 = 1$  and  $\eta_4 = JMAX$  and  $\zeta_4 = KMAX$  is chosen thus ensuring a field size of  $JMAX \times KMAX$  for a given  $\xi$  plane).

In order that the transformed plane contain a uniform grid of spacing equal to unity, the dependent and independent variables

must be interchanged in equations (4a) and (4b). The resulting equations after transformation are as follows:

$$\alpha y_{\eta\eta} - 2\beta y_{\eta\zeta} + \gamma y_{\zeta\zeta} = -J^2 [y_{\eta} Q(\eta, \zeta) + y_{\zeta} R(\eta, \zeta)] \quad (6a)$$

$$\alpha z_{\eta\eta} - 2\beta z_{\eta\zeta} + \gamma z_{\zeta\zeta} = -J^2 [z_{\eta} Q(\eta, \zeta) + z_{\zeta} R(\eta, \zeta)] \quad (6b)$$

where,

$$\alpha = y_{\zeta}^2 + z_{\zeta}^2$$

$$\beta = y_{\eta} y_{\zeta} + z_{\eta} z_{\zeta}$$

$$\gamma = y_{\eta}^2 + z_{\eta}^2$$

$$J = y_{\eta} z_{\zeta} - y_{\zeta} z_{\eta}$$

The boundary conditions transform as follows:

$$\text{on } \Gamma_1^* \quad \begin{bmatrix} y \\ z \end{bmatrix} = \begin{bmatrix} \bar{a}_1(\eta, \zeta_1) \\ \bar{a}_2(\eta, \zeta_1) \end{bmatrix} \quad (7a)$$

$$\text{on } \Gamma_2^* \quad \begin{bmatrix} y \\ z \end{bmatrix} = \begin{bmatrix} \bar{b}_1(\eta_2, \zeta) \\ \bar{b}_2(\eta_2, \zeta) \end{bmatrix} \quad (7b)$$

$$\text{on } \Gamma_3^* \quad \begin{bmatrix} y \\ z \end{bmatrix} = \begin{bmatrix} \bar{c}_1(\eta, \zeta_3) \\ \bar{c}_2(\eta, \zeta_3) \end{bmatrix} \quad (7c)$$

$$\text{and on } \Gamma_4^* \quad \begin{bmatrix} y \\ z \end{bmatrix} = \begin{bmatrix} \bar{d}_1(\eta_4, \zeta) \\ \bar{d}_2(\eta_4, \zeta) \end{bmatrix} \quad (7d)$$

The functions  $\bar{a}_1, \bar{a}_2, \bar{b}_1, \bar{b}_2, \bar{c}_1, \bar{c}_2, \bar{d}_1, \bar{d}_2$  are specified



by known contours  $\Gamma_1, \Gamma_2, \Gamma_3, \Gamma_4$ . If the coordinate point locations on these contours is fixed then dirichlet type boundary conditions can be used. On the other hand if the coordinate lines on these contours is to be made parallel or normal to some line then Neumann type conditions can be used. On  $\Gamma_1^*$  and  $\Gamma_2^*$  dirichlet type conditions were used. On  $\Gamma_3^*$  and  $\Gamma_4^*$  Neumann type conditions were used. Thus the following expressions are obtained on  $\Gamma_3^*$  and  $\Gamma_4^*$ :

on  $\Gamma_3^*$

$$y(J, KMAX) = y(J, KMAX-1) \quad (8a)$$

$$z(J, KMAX) = \text{constant } z_1 \quad (8b)$$

$$1 \leq J \leq JMAX$$

and on  $\Gamma_4^*$

$$z(JMAX, K) = z(JMAX-1, K) \quad (8c)$$

$$y(JMAX, K) = \text{constant } y_1 \quad (8d)$$

$$1 \leq K \leq KMAX$$

The last aspect to be discussed is how Q and R are computed. Q is computed based on the y variation of points on  $\Gamma_1$  and R is computed based on the z variation of points on  $\Gamma_2$ . The following discussion will make this point clearer.

If one assumes on  $\Gamma_1$  that coordinate points are specified such that the y derivatives with respect to  $\zeta$  are zero then from (6a),

$$Q(\eta, \zeta) = - \frac{y_{\eta\eta}}{y_\eta} \quad (9a)$$

Also, Q is not a function of  $\zeta$ . Thus, only one one-dimensional array of size JMAX is sufficient to store Q. Similarly for R we obtain,

$$z_{\zeta\zeta}$$

Again R is not a function of  $\eta$ . A one-dimensional array of size KMAX is sufficient to store R.

#### B. Numerical Solution Technique

Based on the above discussion, the following equations must be numerically solved:

$$\alpha y_{\eta\eta} - 2\beta y_{\eta\zeta} + \gamma y_{\zeta\zeta} = -J^2 [y_{\eta} Q(\eta) + y_{\zeta} R(\zeta)] \quad (10a)$$

$$\alpha z_{\eta\eta} - 2\beta z_{\eta\zeta} + \gamma z_{\zeta\zeta} = -J^2 [z_{\eta} Q(\eta) + z_{\zeta} R(\zeta)] \quad (10b)$$

where

$$Q(\eta) = -\frac{y_{\eta\eta}}{y_{\eta}} \quad \text{on } \Gamma_1 \quad (11a)$$

and

$$R(\zeta) = -\frac{z_{\zeta\zeta}}{z_{\zeta}} \quad \text{on } \Gamma_2 \quad (11b)$$

The first and second order derivatives in (10) and (11) are written in central difference form. The expressions for Q and R are as follows:

$$Q(J) = -\frac{y(J+1,1) - 2*y(J,1) + y(J-1,1)}{(0.5*(y(J+1,1) - y(J-1,1)))**3} \quad (12a)$$

$2 \leq J \leq JMAX-1$

and

$$R(K) = -\frac{z(1,K+1) - 2*z(1,K) + z(1,K-1)}{(0.5*(z(1,K+1) - z(1,K-1)))**3} \quad (12b)$$

$2 \leq K \leq KMAX-1$

Equations (10a) and (10b) are solved by successive over

relaxation (S.O.R) technique. The intermediate value for y and z are as follows:

$$\begin{aligned}\bar{Y}(J,K) = & [\alpha(y(J+1,K) + y(J-1,K)) - 2\beta y_{\eta\zeta} \\ & + \gamma(y(J,K+1) + y(J,K-1)) + J^2(y_{\eta} Q(J) \\ & + y_{\zeta} R(K))] / [2(\alpha+\gamma)]\end{aligned}\quad (13a)$$

where

$$y_{\eta\zeta} = 0.25 [y(J+1,K+1) - y(J+1,K-1) - y(J-1,K+1) + y(J-1,K-1)] \quad (13b)$$

$$y_{\eta} = 0.5 [y(J+1,K) - y(J-1,K)] \quad (13c)$$

$$y_{\zeta} = 0.5 [y(J,K+1) - y(J,K-1)] \quad (13d)$$

$$\alpha = 0.25 [(y(J,K+1) - y(J,K-1))^2 + (z(J,K+1) - z(J,K-1))^2] \quad (13e)$$

$$\begin{aligned}\beta = & 0.25 [(y(J+1,K) - y(J-1,K))(y(J,K+1) - y(J,K-1)) \\ & + (z(J+1,K) - z(J-1,K))(z(J,K+1) - z(J,K-1))]\end{aligned}\quad (13f)$$

$$\gamma = 0.25 [(y(J+1,K) - y(J-1,K))^2 + (z(J+1,K) - z(J-1,K))^2] \quad (13g)$$

$$\begin{aligned}J = & 0.25 [(y(J+1,K) - y(J-1,K))(z(J,K+1) - z(J,K-1)) \\ & - (y(J,K+1) - y(J,K-1))(z(J+1,K) - z(J-1,K))]\end{aligned}\quad (13h)$$

similarly an expression for  $\bar{z}$  can be written out. For each grid

point two finite difference equations (one for  $\bar{y}$  and one for  $\bar{z}$ ) are obtained. The subscripts J and K have a range as follows:

$$J = 2, 3, 4, \dots, JMAX-1$$

$$K = 2, 3, 4, \dots, KMAX-1$$

This results in a set of  $(JMAX-2)(KMAX-2)$ . The above equations are solved simultaneously using S.O.R. For a set of non-linear differential equations for some variable f, S.O.R. iteration can be written as follows:

$$f^{(s+1)} = w \bar{f} + (1 - w) f^{(s)} \quad (14)$$

where superscripts denote the iteration number,  $w$  is the acceleration parameter, and the latest values are used in the difference equations to solve  $\bar{f}$ . In the present problem f denotes y or z.

Since on  $\Gamma_3$  and  $\Gamma_4$ , Neumann type boundary conditions are applied, these conditions are implemented as follows:

on  $\Gamma_3$

$$y(J, KMAX) = y(J, KMAX-1) \quad (15a)$$

$$2 \leq J \leq JMAX$$

on  $\Gamma_4$

$$z(JMAX, K) = z(JMAX-1, K) \quad (15b)$$

$$2 \leq K \leq KMAX$$

Since on  $\Gamma_3$   $z = \text{constant}$  and on  $\Gamma_4$   $y = \text{constant}$ , equations (15a) and (15b) ensure that coordinate lines on  $\Gamma_3$  and  $\Gamma_4$  are orthogonal even though the coordinate system is not necessarily orthogonal everywhere.

### C. Initial Guess and Boundary Point Specification

The input to the program consists of points specification on  $\Gamma_1$  and  $\Gamma_2$  boundary.  $\Gamma_1$  boundary is such that the variation of  $z$  close to the JMAX point is zero. Similarly on  $\Gamma_2$  the  $y$  variation close to KMAX point is zero. Points on  $\Gamma_1$  and  $\Gamma_2$  are specified implied that  $\{y(J,1), z(J,1)\}$   $1 \leq J \leq JMAX$  and  $\{y(1,K), z(1,K)\}$   $1 \leq K \leq KMAX$  are known. Then for the initial guess we have,

$$z(J, KMAX) = z(1, KMAX), \quad 2 \leq J \leq JMAX \quad (16a)$$

$$y(JMAX, K) = y(JMAX, 1), \quad 2 \leq K \leq KMAX \quad (16b)$$

also,

$$y(J, K) = y(1, K) + (y(JMAX, K) - y(1, K)) * ((y(J, 1) - y(1, 1)) / (y(JMAX, 1) - y(1, 1))) \quad (16c)$$

$$z(J, K) = z(J, 1) + (z(J, KMAX) - z(J, 1)) * ((z(1, K) - z(1, 1)) / (z(1, KMAX) - z(1, 1))) \quad (16d)$$

$$2 \leq J \leq JMAX-1 \quad \text{and} \quad 2 \leq K \leq KMAX-1$$

and

$$y(J, KMAX) = y(J, KMAX-1), \quad 2 \leq J \leq JMAX-1 \quad (16e)$$

$$z(JMAX, K) = z(JMAX-1, K), \quad 2 \leq K \leq KMAX-1 \quad (16f)$$

### D. x-Coordinate and Metric Coefficients

As discussed before, the  $y$  and  $z$  variation is computed only for one plane  $\xi = 1$ ; also  $x$  is constant for any specified  $\xi$ -plane. Thus if  $x, y, z$  variation on  $1 \leq \xi \leq IMAX$ ,  $\eta = 1$  and  $\zeta = 1$  is specified then coordinates of any point can be easily specified. For example say for  $\xi = 11$ ,

$$x(I1,1,1) = x1 \quad (17a)$$

$$y(I1,1,1) = y1 \quad (17b)$$

$$z(I1,1,1) = z1 \quad (17c)$$

Then for any point  $I1, J, K$  in  $\xi = I1$  plane we have,

$$x(I1,J,K) = x1 \quad (17d)$$

$$y(I1,J,K) = y(I1,1,1) - y(1,1,1) + y(1,J,K) \quad (17e)$$

$$z(I1,J,K) = z(I1,1,1) - z(1,1,1) + z(1,J,K) \quad (17f)$$

If the coordinate system on  $\xi = 1$  plane is continuous in  $y$  and  $z$ , and if on  $\xi = 1, I_{MAX}, \eta = 1, \zeta = 1$  line the variation in  $x, y, z$  is continuous then the solution given by above equations will be continuous. This is ensured by having continuous  $y$  and  $z$  variation on  $\Gamma_1$  and  $\Gamma_2$  and on line  $\xi = 1, I_{MAX}, \eta = 1, \zeta = 1$ .

A brief discussion on metric coefficients can now be included. The nine metric coefficients  $\beta_{ij}$  are given by:

$$\beta_{11} = (y_\eta z_\zeta - y_\zeta z_\eta)/J \quad (18a)$$

$$\beta_{12} = (y_\zeta z_\xi - y_\xi z_\zeta)/J \quad (18b)$$

$$\beta_{13} = (y_\xi z_\eta - y_\eta z_\xi)/J \quad (18c)$$

$$\beta_{21} = (x_\zeta z_\eta - x_\eta z_\zeta)/J \quad (18d)$$

$$\beta_{22} = (x_\xi z_\zeta - x_\zeta z_\xi)/J \quad (18e)$$

$$\beta_{23} = (x_\eta z_\xi - x_\xi z_\eta)/J \quad (18f)$$

$$\beta_{31} = (x_{\eta} y_{\zeta} - x_{\zeta} y_{\eta})/J \quad (18g)$$

$$\beta_{32} = (x_{\zeta} y_{\xi} - x_{\xi} y_{\zeta})/J \quad (18h)$$

$$\beta_{33} = (x_{\xi} y_{\eta} - x_{\eta} y_{\xi})/J \quad (18i)$$

Since  $x$  is constant for any specified  $\xi$  plane, we have  $x_{\eta} = x_{\zeta} = 0$  which considerably simplifies the above equations. Also, we can ensure that  $y_{\xi} = 0$ ,  $z_{\xi} = 0$  if  $y$  and  $z$  are specified to be constant on  $1 \leq \xi \leq \text{IMAX}$ ,  $\eta = 1$ ,  $\zeta = 1$  line. In such a case the metric coefficients become,

$$\beta_{11} = (y_{\eta} z_{\zeta} - y_{\zeta} z_{\eta})/J \quad (19a)$$

$$\beta_{12} = 0.0 \quad (19b)$$

$$\beta_{13} = 0.0 \quad (19c)$$

$$\beta_{21} = 0.0 \quad (19d)$$

$$\beta_{22} = x_{\xi} z_{\zeta}/J \quad (19e)$$

$$\beta_{23} = -x_{\xi} z_{\eta}/J \quad (19f)$$

$$\beta_{31} = 0.0 \quad (19g)$$

$$\beta_{32} = -x_{\xi} y_{\zeta}/J \quad (19h)$$

$$\beta_{33} = x_{\xi} y_{\eta}/J \quad (19i)$$



$$J = x_{\xi} (y_{\eta} z_{\zeta} - y_{\zeta} z_{\eta}) \quad (19j)$$

#### E. Concluding Remarks

A method for generating 3-D body-fitted coordinate system for corner flows has been presented. The computer code to generate coordinate systems using equations 12, 13, 14, 15, 16 is presented in Chapter 3. The generated coordinate system is stored on a disk file which becomes a part of the input to the Navier Stokes code. Successful coordinate systems for corners

with or without fillet and for a 3-D flat plate have been generated (the program can generate suitable coordinate systems for a 3-D flat plate problem). The compressible laminar Navier Stokes solution for the above mentioned problems at low Reynolds number have already been obtained. Effort is now underway to obtain solution for higher Reynolds number with or without turbulence.





## II. Computer Program

### A. Listing of the Computer Program

The program listing follows this page.

```

**** *DECK CORD1
      PROGRAM COORDC(INPUT,OUTPUT,SOLNXX,TAPE1=SOLNXX,TAPE5=INPUT,
1      TAPE6=OUTPUT)
C**
C*****
C**
C**      CORNER COORDINATE GENERATION PROGRAM BASED ON METHOD
C**      DEVELOPED BY THOMPSON, THAMES, AND MASTIN OF MISSISSIPPI
C**      STATE UNIVERSITY.
C**
C**      FOR FURTHER ENQUIRIES CONTACT :
C**
C**      DR. JULIUS HARRIS
C**      DR. DILIP KUMAR
C**      NASA - LANGLEY RESEARCH CENTER
C**      MAIL STOP 163
C**      HAMPTON, VA. 23665
C**      PHONE: 804-827-3696
C**      FTS CODE 928-1110
C**
C*****
C**
C**      THIS PROGRAM GENERATES COORDINATE SYSTEM FOR A 2-D CORNER
C**      WITH OR WITHOUT FILLER. THE METHOD USED IS BASED ON METHOD
C**      DEVELOPED BY THOMPSON, THAMES, MASTIN AND OTHERS AT MISS.
C**      STATE UNIVERSITY. THE CORNER IS SUCH THAT EXCEPT IN THE
C**      FILLER (WHEN PRESENT) L.H.S. BOUNDARY HAS  $Z = 0$  AND BOTTOM
C**      SIDE BOUNDARY HAS  $Y = 0$ . ALSO R.H.S. BOUNDARY ALWAYS HAS
C**       $Z = \text{CONSTANT}$  AND UPPER BOUNDARY HAS  $Y = \text{CONSTANT}$ . THE
C**      PROGRAM GENERATES Q AND R SUCH THAT COORDINATE CLUSTERING
C**      IS PROPORTIONAL TO COORDINATE POINTS DISTRIBUTION ON L.H.S.
C**      AND BOTTOM BOUNDARY. ON R.H.S. AND TOP BOUNDARIES NEUMANN
C**      TYPE BOUNDARY CONDITIONS ARE USED. THIS ENSURES THAT
C**      COORDINATE LINES ON R.H.S. AND UPPER BOUNDARY ARE PARALLEL
C**      TO SIDES.
C**
C**
C**
C**
C**      --- CARD INPUT ---
C**
C**      CARD1: SPECIFIES FIELD SIZE AND PRINT, PLOT FLAGS
C**      JMAX,KMAX,IPRT1,IPRT2,IPLT1,IPLT2,ITERMX,R1,R2,R3
C**      (FORMAT 7I5,5X,3F10.0)

```

```

CORD1 1
CORD1 2
CORD1 3
CORD1 4
CORD1 5
CORD1 6
CORD1 7
CORD1 8
CORD1 9
CORD1 10
CORD1 11
CORD1 12
CORD1 13
CORD1 14
CORD1 15
CORD1 16
CORD1 17
CORD1 18
CORD1 19
CORD1 20
CORD1 21
CORD1 22
CORD1 23
CORD1 24
CORD1 25
CORD1 26
CORD1 27
CORD1 28
CORD1 29
CORD1 30
CORD1 31
CORD1 32
CORD1 33
CORD1 34
CORD1 35
CORD1 36
CORD1 37
CORD1 38
CORD1 39
CORD1 40
CORD1 41
CORD1 42
CORD1 43
CORD1 44

```

C\*\* JMAX : NO OF NODES IN Y-DIRECTION  
C\*\* KMAX : NO OF NODES IN Z-DIRECTION  
C\*\* IPRT1 : INITIAL GUESS IS TO BE PRINTED OR NOT  
C\*\* IF IPRT1 = 1 THEN PARTIALLY CONVERGED  
C\*\* SOLUTION IS PRINTED EVERY 50 ITER.  
C\*\* IPRT2 : FINAL SOLUTION TO BE PRINTED OR NOT  
C\*\* IPLT1 : INITIAL GUESS TO BE PLOTTED OR NOT  
C\*\* IPLT2 : FINAL SOLUTION TO BE PLOTTED OR NOT  
C\*\* ITERMX : MAXIMUM NO. OF ITERATIONS ALLOWED  
C\*\* R1 : GAUSS SEIDELL ITERATION PARAMETER  
C\*\* (USUALLY 0.6)  
C\*\* R2 : CONVERGENCE CRITERION IN Y-DIRECTION  
C\*\* (USUALLY 0.000005 TO 0.00001)  
C\*\* R3 : CONVERGENCE CRITERION IN Z-DIRECTION  
C\*\* (USUALLY SAME AS R2)  
C\*\*  
C\*\* NOTE : FOR ALL FLAGS 0 MEANS NO, 1 MEANS YES  
C\*\*  
C\*\* CARD2: CARDS TO SPECIFY POINT DISTRIBUTION ON L.H.S.  
C\*\* BOUNDARY (Y-DIRECTION) NO OF CARDS = JMAX  
C\*\* Y,Z (FORMAT 2F10.0)  
C\*\* Y : Y COORDINATE  
C\*\* Z : Z COORDINATE  
C\*\*  
C\*\* CARD3: CARDS TO SPECIFY POINT DISTRIBUTION ON BOTTOM  
C\*\* BOUNDARY (Z-DIRECTION). NO. OF CARDS = KMAX.  
C\*\* Y,Z (FORMAT 2F10.0) SEE CARD TYPE 2)  
C\*\*  
C\*\* CARD4: SPECIFIES NO. OF NODES IN X-DIRECTION.  
C\*\* IMAX (FORMAT(I5)  
C\*\* IMAX : NO. OF POINTS IN X-DIRECTION.  
C\*\*  
C\*\* CARD5: CARDS TO SPECIFY NO. OF POINTS IN X - DIRECTION.  
C\*\* X,Y1,Z1 (FORMAT 3F10.0)  
C\*\* X : X-COORDINATE ON J=1,K=1 LINE (X-DIRECTION)  
C\*\* Y1 : Y-COORDINATE ON J=1,K=1 LINE (X-DIRECTION)  
C\*\* Z1 : Z-COORDINATE ON J=1,K=1 LINE (X-DIRECTION)  
C\*\*  
C\*\* CARD6: PRINT,PLOT HEADINGS.  
C\*\* HED1(4) (FORMAT 4A10)  
C\*\* HED1 : 40 BYTES OF PLOT HEADING  
C\*\*  
C\*\* CARD7: ADDITIONAL PRINT PLOT HEADINGS.  
C\*\* HED2(4) (FORMAT 4A10)

CORD1 45  
CORD1 46  
CORD1 47  
CORD1 48  
CORD1 49  
CORD1 50  
CORD1 51  
CORD1 52  
CORD1 53  
CORD1 54  
CORD1 55  
CORD1 56  
CORD1 57  
CORD1 58  
CORD1 59  
CORD1 60  
CORD1 61  
CORD1 62  
CORD1 63  
CORD1 64  
CORD1 65  
CORD1 66  
CORD1 67  
CORD1 68  
CORD1 69  
CORD1 70  
CORD1 71  
CORD1 72  
CORD1 73  
CORD1 74  
CORD1 75  
CORD1 76  
CORD1 77  
CORD1 78  
CORD1 79  
CORD1 80  
CORD1 81  
CORD1 82  
CORD1 83  
CORD1 84  
CORD1 85  
CORD1 86  
CORD1 87  
CORD1 88

```

C**      HE02      1 40 BYTES OF ADDITIONAL PLOT HEADING.
C**
C**      SAMPLE RUNSTREAM.
C**
C**      KVIS2,T777,CM70000.      BIN 34      D KUMAR
C**      USER,479019C.
C**      CHARGE,100718,LRC.
C**      GET(OLDPL=KHRC01/UN=375732N).
C**      UPDATE(F,C=VISFL1).
C**      COPY8R,INPUT,EDTFT1.
C**      REWIND,VISFL1,EDTFT1.
C**      EDIT,VISFL1,I=EDTFT1.
C**      REWIND,VISFL1.
C**      FTN(OPT=1,I=VISFL1).
C**      ATTACH,LRCGOSF/UN=LIBRARY,NA.
C**      LDSET,LIB=LRCGOSF,PRESET=ZERO.
C**      LGO.
C**      PLOT,VARIAN
C**      REWIND,SOLNXX.
C**      COPY8R,SOLNXX,FILETC.
C**      REWIND,FILETC.
C**      SAVE,FILETC.
C**      7/8/9
C**      *IDENT DUM1
C**      *INSERT CORD1.3
C**      C**
C**      7/8/9
C**      RS:// MXLL/,/ 30/;*
C**      RS:// MXLL/,/ 23/;*
C**      RS:// MXLL/,/ 23/;*
C**      END
C**      7/8/9
C**      INPUT DATA.  SEE EXPLANATION ABOVE.
C**      6/7/8/9
C**
C**      REWIND,VISFL1.
C**      NOTE: AFTER FIRST 7/8/9 CARD 3 CARDS ARE INPUT TO
C**            SATISFY INPUT FOR UPDATE UTILITY.
C**
C**      AFTER 2ND 7/8/9 CARD EDIT CARDS ARE INPUT.  THE
C**      PROGRAM IS WRITTEN SO THAT MAXIMUM NUMBER OF

```

```

CORD1      89
CORD1      90
CORD1      91
CORD1      92
CORD1      93
CORD1      94
CORD1      95
CORD1      96
CORD1      97
CORD1      98
CORD1      99
CORD1     100
CORD1     101
CORD1     102
CORD1     103
CORD1     104
CORD1     105
CORD1     106
CORD1     107
CORD1     108
CORD1     109
CORD1     110
CORD1     111
CORD1     112
CORD1     113
CORD1     114
CORD1     115
CORD1     116
CORD1     117
CORD1     118
CORD1     119
CORD1     120
CORD1     121
CORD1     122
CORD1     123
CORD1     124
CORD1     125
CORD1     126
CORD1     127
CORD1     128
CORD1     129
CORD1     130
CORD1     131
CORD1     132

```

C\*\* POINTS IN X,Y,Z DIRECTION CAN BE CHANGED BY SIMPLE  
 C\*\* INPUT. IN THE ABOVE CASE FIELD SIZE OF 30,23,23  
 C\*\* IS ASSUMED. IN THE THREE CARDS AFTER RS1/ AND MXLL  
 C\*\* I,J,K SHOULD BE INPUT RESPECTIVELY. THIS COULD NOT  
 C\*\* BE SHOWN ABOVE BECAUSE TEXT EDITOR CHANGES TEXT IN  
 C\*\* COMMENTS CARDS ALSO.

C\*\* IT IS ASSUMED THAT PROGRAM RESIDES ON FILE KMRC01  
 C\*\* UNDER USER NO. OF 375732N AND USER 479019C HAS  
 C\*\* PERMISSION TO USE IT. FURTHERMORE, IT IS ALSO ASSUMED  
 C\*\* THAT THE COORDINATE SYSTEM SOLUTION IS TO BE STORED  
 C\*\* ON FILE FILETC. THIS NAME CAN BE CHANGED BY  
 C\*\* CHANGING THREE CARDS TOWARDS THE END OF THE RUNSTREAM.

C\*\* THE PLOTS ON CALCOMP CAN BE OBTAINED BY REPLACING  
 C\*\* PLOT.VARIAN CARD BY FOLLOWING CARDS.  
 C\*\* PLOT.CALPOST,11(XO=1.0,YO=0.2)  
 C\*\* CONT. //PAPER 00,  
 C\*\* CONT. LEROY PEN SIZE 0.3  
 C\*\* CONT. MULTIPLE PLOT MODE  
 C\*\* CONT. THESE PLOTS ARE FOR REPORTS//

C\*\* COMMON /BXXX/ Y(JMXLL,KMXLL),Z(JMXLL,KMXLL),Q(JMXLL),R(KMXLL),  
 1 X(IMXLL),Y1(IMXLL),Z1(IMXLL)  
 C\*\* COMMON /AXXX/ ILIMIT,JLIMIT,KLIMIT,IMAX,JMAX,KMAX,IPRT1,IPRT2,  
 1 IPLT1,IPLT2,ITERMX,R1,R2,R3,I1,HED1(4),HED2(4)  
 C\*\* DATA KKK,YERRMX,ZERRMX,I1,IYLOCJ,IYLOCK,IZLOCJ,IZLOCK /0,2+0.,5+0/  
 C\*\* ILIMIT = IMXLL  
 C\*\* JLIMIT = JMXLL  
 C\*\* KLIMIT = KMXLL

C\*\* INITIALIZE Q,R,Y AND Z TO ZERO.

DO 10 J = 1,JLIMIT  
 Q(J) = 0.0  
 10 CONTINUE  
 DO 20 K = 1,KLIMIT  
 R(K) = 0.0  
 20 CONTINUE  
 DO 30 J = 1,JLIMIT  
 DO 30 K = 1,KLIMIT  
 Y(J,K) = 0.0

CORD1 133  
 CORD1 134  
 CORD1 135  
 CORD1 136  
 CORD1 137  
 CORD1 138  
 CORD1 139  
 CORD1 140  
 CORD1 141  
 CORD1 142  
 CORD1 143  
 CORD1 144  
 CORD1 145  
 CORD1 146  
 CORD1 147  
 CORD1 148  
 CORD1 149  
 CORD1 150  
 CORD1 151  
 CORD1 152  
 CORD1 153  
 CORD1 154  
 CORD1 155  
 CORD1 156  
 CORD1 157  
 CORD1 158  
 CORD1 159  
 CORD1 160  
 CORD1 161  
 CORD1 162  
 CORD1 163  
 CORD1 164  
 CORD1 165  
 CORD1 166  
 CORD1 167  
 CORD1 168  
 CORD1 169  
 CORD1 170  
 CORD1 171  
 CORD1 172  
 CORD1 173  
 CORD1 174  
 CORD1 175  
 CORD1 176

```

      Z(J,K) = 0.0
30  CONTINUE
C**
C**      READ INPUT
C**
      READ(5,1000) JMAX,KMAX,IPRT1,IPRT2,IPLT1,IPLT2,ITERMX,R1,R2,R3
      IF(JMAX.GT.JLIMIT.OR.KMAX.GT.KLIMIT) GO TO 50
      GO TO 60
C**
50  WRITE(6,1020) JMAX,KMAX,JLIMIT,KLIMIT
      CALL EXIT
C**
60  CONTINUE
      READ(5,1030) ((Y(J,1),Z(J,1)),J=1,JMAX)
      READ(5,1030) ((Y(1,K),Z(1,K)),K=1,KMAX)
C**
C**      READ IN POINTS ALONG J = 1, K = 1 LINE (X-DIRECTION)
C**
      READ(5,1000) IMAX
      IF(IMAX.LE.ILIMIT) GO TO 65
      WRITE(6,1090) IMAX,ILIMIT
      STOP
65  CONTINUE
C**
      READ(5,1100) ((X(I),Y1(I),Z1(I)),I=1,IMAX)
C**
C**      SPECIFY INITIAL GUESS ON THE WHOLE FIELD
C**
      DO 70 J = 2,JMAX
        Z(J,KMAX) = Z(1,KMAX)
70  CONTINUE
      DO 80 K = 2,KMAX
        Y(JMAX,K) = Y(JMAX,1)
80  CONTINUE
C**
      J1 = JMAX - 1
      K1 = KMAX - 1
      DO 100 J = 2,J1
        DO 100 K = 2,K1
          Y(J,K) = (Y(JMAX,K) - Y(1,K)) * ((Y(J,1) - Y(1,1)) /
1          (Y(JMAX,1) - Y(1,1))) + Y(1,K)
          Z(J,K) = (Z(J,KMAX) - Z(J,1)) * ((Z(1,K) - Z(1,1)) /
1          (Z(1,KMAX) - Z(1,1))) + Z(J,1)
100 CONTINUE

```

```

CORD1 177
CORD1 178
CORD1 179
CORD1 180
CORD1 181
CORD1 182
CORD1 183
CORD1 184
CORD1 185
CORD1 186
CORD1 187
CORD1 188
CORD1 189
CORD1 190
CORD1 191
CORD1 192
CORD1 193
CORD1 194
CORD1 195
CORD1 196
CORD1 197
CORD1 198
CORD1 199
CORD1 200
CORD1 201
CORD1 202
CORD1 203
CORD1 204
CORD1 205
CORD1 206
CORD1 207
CORD1 208
CORD1 209
CORD1 210
CORD1 211
CORD1 212
CORD1 213
CORD1 214
CORD1 215
CORD1 216
CORD1 217
CORD1 218
CORD1 219
CORD1 220

```

```

DO 102 J = 2,J1
  Y(J,KMAX) = Y(J,KMAX-1)
102 CONTINUE
DO 104 K = 2,K1
  Z(JMAX,K) = Z(JMAX-1,K)
104 CONTINUE
C**
C**      READ PRINT,PLOT HEADINGS. TWO CARDS ARE READ IN.
C**      CALL PLOT INITIALIZING ROUTINE PSEUDO IF PLOT OPTIONS
C**      SET.
C**
READ(5,1080) (HED1(I),I=1,4)
READ(5,1080) (HED2(I),I=1,4)
IF(IPLT1.EQ.0.AND.IPLT2.EQ.0) GO TO 110
  CALL PSEUDO
  CALL FONTS(1)
110 CONTINUE
C**
C**      SEE IF INITIAL GUESS NEEDS TO BE PRINTED
C**
IF(IPRT1.EQ.1) CALL IPRTC(1,KKK,YERRMX,ZERRMX, IYLOCJ,IYLOCK,
1 IZLOCJ,IZLOCK)
C**
C**      SEE IF INITIAL GUESS NEED TO BE PLOTTED
C**
IF(IPLT1.EQ.1) CALL IPLTC(1,KKK,YERRMX,ZERRMX, IYLOCJ,IYLOCK,
1 IZLOCJ,IZLOCK)
C**
C**      COMPUTE Q AND R. FIRST YETA OR ZTAU IS COMPUTED.
C**      Q = - YETAETA / (YETA*YETA*YETA)
C**      R = - ZTAUTAU / (ZTAU*ZTAU*ZTAU)
C**
DO 120 J = 2,J1
  A1 = 0.5 * (Y(J+1,1) - Y(J-1,1))
  Q(J) = - (Y(J+1,1) - 2.0*Y(J,1) + Y(J-1,1)) / (A1*A1*A1)
120 CONTINUE
C**
DO 140 K = 2,K1
  A1 = 0.5 * (Z(1,K+1) - Z(1,K-1))
  R(K) = - (Z(1,K+1) - 2.0*Z(1,K) + Z(1,K-1)) / (A1*A1*A1)
140 CONTINUE
C**
C**      START COMPUTING SOLUTION.
C**

```

```

CORD1 221
CORD1 222
CORD1 223
CORD1 224
CORD1 225
CORD1 226
CORD1 227
CORD1 228
CORD1 229
CORD1 230
CORD1 231
CORD1 232
CORD1 233
CORD1 234
CORD1 235
CORD1 236
CORD1 237
CORD1 238
CORD1 239
CORD1 240
CORD1 241
CORD1 242
CORD1 243
CORD1 244
CORD1 245
CORD1 246
CORD1 247
CORD1 248
CORD1 249
CORD1 250
CORD1 251
CORD1 252
CORD1 253
CORD1 254
CORD1 255
CORD1 256
CORD1 257
CORD1 258
CORD1 259
CORD1 260
CORD1 261
CORD1 262
CORD1 263
CORD1 264

```



```

      KKK = 0
      IERR = 0
      DO 500 I1 = 1, ITERMX
        YERRMX = 0.0
        ZERRMX = 0.0
        CALL CALCOR(YERRMX, ZERRMX, IYLOCJ, IYLOCK, IZLOCJ, IZLOCK)
C**
C**      CHECK IF MAX ERROR TO BE PRINTED OR NOT
C**
      IERR = IERR + 1
      IF(IERR.NE.50) GO TO 160
      IERR = 0
      WRITE(6,1040) I1, IYLOCJ, IYLOCK, YERRMX, IZLOCJ, IZLOCK, ZERRMX
      IF(IPRT1.EQ.1) CALL IPRTC(2, KKK, YERRMX, ZERRMX, IYLOCJ, IYLOCK,
1      IZLOCJ, IZLOCK)
160    CONTINUE
C**
C**      CHECK FOR CONVERGENCE
C**
      IF(YERRMX.GT.R2) GO TO 180
      IF(ZERRMX.GT.R3) GO TO 180
C**
C**      SOLUTION CONVERGED. GET OUT OF THE LOOP. KKK = 1
C**      INDICATES SOLUTION CONVERGED
C**
      KKK = 1
      GO TO 520
C**
180    .CONTINUE
500  CONTINUE
520  CONTINUE
C**
C**      SEE IF CONVERGED OR PARTIALLY CONVERGED SOLUTION IS TO
C**      BE PLOTTED AND PRINTED OR NOT
C**
      IF(IPRT2.EQ.1) CALL IPRTC(2, KKK, YERRMX, ZERRMX, IYLOCJ, IYLOCK,
1      IZLOCJ, IZLOCK)
C**
      IF(IPLT2.EQ.1) CALL IPLTC(2, KKK, YERRMX, ZERRMX, IYLOCJ, IYLOCK,
1      IZLOCJ, IZLOCK)
C**
C**      STORE CONVERGED SOLUTION
C**
      IF(KKK.EQ.0) GO TO 540

```

```

CORD1 265
CORD1 266
CORD1 267
CORD1 268
CORD1 269
CORD1 270
CORD1 271
CORD1 272
CORD1 273
CORD1 274
CORD1 275
CORD1 276
CORD1 277
CORD1 278
CORD1 279
CORD1 280
CORD1 281
CORD1 282
CORD1 283
CORD1 284
CORD1 285
CORD1 286
CORD1 287
CORD1 288
CORD1 289
CORD1 290
CORD1 291
CORD1 292
CORD1 293
CORD1 294
CORD1 295
CORD1 296
CORD1 297
CORD1 298
CORD1 299
CORD1 300
CORD1 301
CORD1 302
CORD1 303
CORD1 304
CORD1 305
CORD1 306
CORD1 307
CORD1 308

```

```

WRITE(1,1110) ILIMIT,JLIMIT,KLIMIT,IMAX,JMAX,KMAX,
1 ((HED1(I),HED2(I)),I=1,4)
WRITE(1,1120) (((Y(J,K),Z(J,K)),K=1,KLIMIT),J=1,JLIMIT)
WRITE(1,1120) ((X(I),Y1(I),Z1(I)),I=1,ILIMIT)
GO TO 560

C**
C**      SOLUTION DID NOT CONVERGE. WRITE A MESSAGE
C**
540 CONTINUE
WRITE(6,1060) YERRMX,IYLOCJ,IYLOCK,ZERRMX,IZLOCJ,IZLOCK,R2,R3,
1 ITERMX

C**
C**      ALL FUNCTIONS COMPLETE
C**
560 CONTINUE
STOP

C**
C**      FORMAT STATEMENTS
C**
1000 FORMAT(7I5,5X,3F10.0)
1020 FORMAT("1"///5X,"*** NO OF POINTS IN Y OR Z GREATER THAN",
1 " MAXIMUM ALLOWED."//5X,"*** POINTS INPUT = ",2I5,/,5X,
2 " MAXIMUM ALLOWED = ",2I5,/,5X,"*** RUN ABORTED")
1030 FORMAT(2F10.0)
1040 FORMAT("0",5X,"ITER NO.,IYLOCJ,IYLOCK,YERRMX,IZLOCJ,IZLOCK,",
1 "ZERRMX = ",3I5,E15.6,2I5,E15.6 )

C**
1060 FORMAT("1"///5X,"*** SOLUTION DID NOT CONVERGE. SOLUTION",
1 " NOT STORED ON UNIT 1"//5X,"*** MAX ERROR IN Y = ",E15.6,
2 " OCCURED AT LOCATION = ",I5,"",I5//5X,"*** MAX ERROR IN "
3 "Z = ",E15.6," OCCURED AT LOCATION = ",I5,"",I5//5X,
4 "*** MAX ERROR ALLOWED IN Y AND Z = ",2E15.6//5X,"*** NO.",
5 " OF ITERATIONS PERFORMED = ",I5)
1080 FORMAT(4A10)
1090 FORMAT("1"///5X,"*** NO. OF POINTS IN X-DIRECTION GREATER THAN",
1 " MAXIMUM ALLOWED."//5X,"*** POINTS INPUT = ",I5,/,5X,
2 " MAXIMUM ALLOWED = ",I5//5X,"*** RUN ABORTED.")
1100 FORMAT(3F10.0)
1110 FORMAT(6I5,8A10)
1120 FORMAT(1X,8E15.8)

C**
C**
END
SUBROUTINE CALCOR(YERRMX,ZERRMX,IYLOCJ,IYLOCK,IZLOCJ,IZLOCK)

```

```

CORD1 309
CORD1 310
CORD1 311
CORD1 312
CORD1 313
CORD1 314
CORD1 315
CORD1 316
CORD1 317
CORD1 318
CORD1 319
CORD1 320
CORD1 321
CORD1 322
CORD1 323
CORD1 324
CORD1 325
CORD1 326
CORD1 327
CORD1 328
CORD1 329
CORD1 330
CORD1 331
CORD1 332
CORD1 333
CORD1 334
CORD1 335
CORD1 336
CORD1 337
CORD1 338
CORD1 339
CORD1 340
CORD1 341
CORD1 342
CORD1 343
CORD1 344
CORD1 345
CORD1 346
CORD1 347
CORD1 348
CORD1 349
CORD1 350
CORD1 351
CORD1 352

```

```

C**
C**      THIS SUBROUTINE ITERATES FOR COORDINATE SYSTEM SOLUTION.
C**      THE SUBROUTINE IS CALLED FROM COORDC PROGRAM
C**
COMMON /BXXX/ Y(JMXLL,KMXLL),Z(JMXLL,KMXLL),Q(JMXLL),R(KMXLL),
1  X(IMXLL),Y1(IMXLL),Z1(IMXLL)
COMMON /AXXX/ ILIMIT,JLIMIT,KLIMIT,IMAX,JMAX,KMAX,IPRT1,IPRT2,
1  IPLT1,IPLT2,ITERMX,R1,R2,R3,I1,HED1(4),HED2(4)
C**
C**      COMPUTE IN INNER FIELDS
C**
J1 = JMAX - 1
K1 = KMAX - 1
DO 200 J = 2,J1
DO 200 K = 2,K1
  YPOPO = Y(J,K)
  YPOP1 = Y(J,K+1)
  YPOM1 = Y(J,K-1)
  YP1PO = Y(J+1,K)
  YM1PO = Y(J-1,K)
  YM1M1 = Y(J-1,K-1)
  YM1P1 = Y(J-1,K+1)
  YP1M1 = Y(J+1,K-1)
  YP1P1 = Y(J+1,K+1)
  ZPOPO = Z(J,K)
  ZPOP1 = Z(J,K+1)
  ZPOM1 = Z(J,K-1)
  ZP1PO = Z(J+1,K)
  ZM1PO = Z(J-1,K)
  ZM1M1 = Z(J-1,K-1)
  ZM1P1 = Z(J-1,K+1)
  ZP1M1 = Z(J+1,K-1)
  ZP1P1 = Z(J+1,K+1)
  QOQ = Q(J)
  RRR = R(K)
  ALPHA = 0.25*((YPOP1 - YPOM1)**2.0 + (ZPOP1 - ZPOM1)**2.0)
  BETA = 0.25*((YP1PO - YM1PO) * (YPOP1 - YPOM1) +
1  (ZP1PO - ZM1PO) * (ZPOP1 - ZPOM1))
  GAMMA = 0.25*((YP1PO - YM1PO)**2.0 + (ZP1PO - ZM1PO)**2.0)
  AJCB1 = 0.25*((YP1PO - YM1PO) * (ZPOP1 - ZPOM1) -
1  (YPOP1 - YPOM1) * (ZP1PO - ZM1PO))
C**
YYY1 = (0.5 * ALPHA * (YP1PO + YM1PO) - 0.25 * BETA *
1  (YP1P1 - YP1M1 - YM1P1 + YM1M1) + 0.5 * GAMMA *

```

```

CORD1 353
CORD1 354
CORD1 355
CORD1 356
CORD1 357
CORD1 358
CORD1 359
CORD1 360
CORD1 361
CORD1 362
CORD1 363
CORD1 364
CORD1 365
CORD1 366
CORD1 367
CORD1 368
CORD1 369
CORD1 370
CORD1 371
CORD1 372
CORD1 373
CORD1 374
CORD1 375
CORD1 376
CORD1 377
CORD1 378
CORD1 379
CORD1 380
CORD1 381
CORD1 382
CORD1 383
CORD1 384
CORD1 385
CORD1 386
CORD1 387
CORD1 388
CORD1 389
CORD1 390
CORD1 391
CORD1 392
CORD1 393
CORD1 394
CORD1 395
CORD1 396

```

```

2      (YPOPI + YPOMI) + 0.25 * AJCB1 * AJCB1 * ((YP1PO - YM1PO) *
3      QOO + (YPOPI - YPOMI) * RRR) / (ALPHA + GAMMA)
C**
      ZZZ1 = (0.5 * ALPHA * (ZP1PO + ZM1PO) - 0.25 * BETA *
1      (ZP1P1 - ZP1M1 - ZM1P1 + ZM1M1) + 0.5 * GAMMA * (ZPOPI
2      + ZPOMI) + 0.25 * AJCB1 * AJCB1 * ((ZP1PO - ZM1PO) * QOO +
3      (ZPOPI - ZPOMI) * RRR) / (ALPHA + GAMMA)
C**
C**      INTERMEDIATE VALUE CALCULATED. COMPUTE NEW VALUE USING
C**      GAUSS SEIDELL ITERATION
C**
      YYY1 = R1 * YYY1 + (1.0 - R1) * YPOPO
      ZZZ1 = R1 * ZZZ1 + (1.0 - R1) * ZPOPO
C**
C**      FIND MAX ERROR AND ITS LOCATION
C**
      ERR1 = ABS(YYY1 - YPOPO)
      IF(ERR1.LE. YERRMX) GO TO 30
      IYLOCJ = J
      IYLOCK = K
      YERRMX = ERR1
30     CONTINUE
C**
      ERR1 = ABS(ZZZ1 - ZPOPO)
      IF(ERR1.LE. ZERRMX) GO TO 60
      IZLOCJ = J
      IZLOCK = K
      ZERRMX = ERR1
60     CONTINUE
C**
C**      SET NEW VALUES
C**
      Y(J,K) = YYY1
      Z(J,K) = ZZZ1
C**
200    CONTINUE
C**
C**      APPLY NEUMANN CONDITIONS ON R.H.S. AND UPPER BOUNDARY
C**
      DO 220 K = 2,K1
          Z(JMAX,K) = Z(JMAX-1,K)
220    CONTINUE
C**
      DO 240 J = 2,J1

```

CORD1	397
CORD1	398
CORD1	399
CORD1	400
CORD1	401
CORD1	402
CORD1	403
CORD1	404
CORD1	405
CORD1	406
CORD1	407
CORD1	408
CORD1	409
CORD1	410
CORD1	411
CORD1	412
CORD1	413
CORD1	414
CORD1	415
CORD1	416
CORD1	417
CORD1	418
CORD1	419
CORD1	420
CORD1	421
CORD1	422
CORD1	423
CORD1	424
CORD1	425
CORD1	426
CORD1	427
CORD1	428
CORD1	429
CORD1	430
CORD1	431
CORD1	432
CORD1	433
CORD1	434
CORD1	435
CORD1	436
CORD1	437
CORD1	438
CORD1	439
CORD1	440

```

      Y(J,KMAX) = Y(J,KMAX-1)
240 CONTINUE
C**
      RETURN
      END
      SUBROUTINE IPRTC(ISOLN, KKK, YERRMX, ZERRMX, IYLOCJ, IYLOCK,
1      IZLOCJ, IZLOCK)
C**
C**      THIS SUBROUTINE PRINTS THE COORDINATE SYSTEM IN Y AND Z
C**      PLANE. ISOLN = 1 INDICATES INITIAL GUESS IS TO BE PRINTED.
C**      ISOLN = 2 INDICATES INDICATES CONVERGED OR PARTIALLY
C**      CONVERGED SOLUTION IS TO BE PRINTED. KKK = 0 INDICATES
C**      PARTIALLY CONVERGED SOLUTION AND KKK = 1 INDICATES CONVERGED
C**      SOLUTION
C**
      COMMON /BXXX/ Y(JMXLL,KMXLL), Z(JMXLL,KMXLL), O(JMXLL), R(KMXLL),
1      X(IMXLL), Y1(IMXLL), Z1(IMXLL)
      COMMON /AXXX/ ILIMIT, JLIMIT, KLIMIT, IMAX, JMAX, KMAX, IPRT1, IPRT2,
1      IPLT1, IPLT2, ITERMX, R1, R2, R3, I1, HED1(4), HED2(4)
C**
C**      PRINT HEADINGS
C**
      IF(ISOLN.EQ.1) WRITE(6,1000)
      IF(ISOLN.EQ.2.AND.KKK.EQ.0) WRITE(6,1010)
      IF(ISOLN.EQ.2.AND.KKK.EQ.1) WRITE(6,1020)
      WRITE(6,1025) HED1
      WRITE(6,1025) HED2
      WRITE(6,1030) JMAX, KMAX
      IF(ISOLN.EQ.1) GO TO 50
      WRITE(6,1040) I1
      WRITE(6,1050) YERRMX, IYLOCJ, IYLOCK
      WRITE(6,1060) ZERRMX, IZLOCJ, IZLOCK
50 CONTINUE
C**
C**      PRINT ARRAYS
C**
      DO 100 J = 1, JMAX
      WRITE(6,1070) J
      WRITE(6,1080) ((Y(J,K), Z(J,K)), K = 1, KMAX)
100 CONTINUE
C**
C**      PRINT J=1, K=1, I=1, IMAX
C**
      WRITE(6,1200)

```

```

CORD1 441
CORD1 442
CORD1 443
CORD1 444
CORD1 445
CORD1 446
CORD1 447
CORD1 448
CORD1 449
CORD1 450
CORD1 451
CORD1 452
CORD1 453
CORD1 454
CORD1 455
CORD1 456
CORD1 457
CORD1 458
CORD1 459
CORD1 460
CORD1 461
CORD1 462
CORD1 463
CORD1 464
CORD1 465
CORD1 466
CORD1 467
CORD1 468
CORD1 469
CORD1 470
CORD1 471
CORD1 472
CORD1 473
CORD1 474
CORD1 475
CORD1 476
CORD1 477
CORD1 478
CORD1 479
CORD1 480
CORD1 481
CORD1 482
CORD1 483
CORD1 484

```

```

WRITE(6,1210) ((X(I),Y1(I),Z1(I)),I=1,IMAX)
C**
C**      FORMAT STATEMENTS
C**
1000 FORMAT("1//51X,"*** INITIAL SOLUTION ***")
1010 FORMAT("1//44X,"*** PARTIALLY CONVERGED SOLUTION ***")
1020 FORMAT("1//49X,"*** CONVERGED SOLUTION ***")
1025 FORMAT(" ",42X,4A10)
1030 FORMAT("0",50X,"JMAX = ",I5,4X,"KMAX = ",I5)
1040 FORMAT(" ",47X,"MAX ITERATIONS PERFORMED = ",I5)
1050 FORMAT(" ",37X,"MAX Y-ERROR = ",E15.6,2X,"AT LOC. J,K = ",I5,
1      " ",I5)
1060 FORMAT(" ",37X,"MAX Z-ERROR = ",E15.6,2X,"AT LOC. J,K = ",I5,
1      " ",I5)
1070 FORMAT(/1X, "J = ",I5," (Y-Z ARRAY)")
1080 FORMAT(1X,E11.5,2X,E11.5,2X,E11.5,2X,E11.5,2X,E11.5,2X,E11.5,
1      2X,E11.5,2X,E11.5,2X,E11.5,2X,E11.5)
1200 FORMAT(/1X, "J=1,K=1,X=1,IMAX (X,Y,Z ARRAY)")
1210 FORMAT(1X,E11.5,2X,E11.5,2X,E11.5,2X,E11.5,2X,E11.5,2X,
1      E11.5,2X,E11.5,2X,E11.5,2X,E11.5)
C**
C**      ALL FUNCTIONS COMPLETE
C**
RETURN
END
SUBROUTINE IPLTC(ISOLN,KKK,YERRMX,ZERRMX,IYLOCJ,IYLOCK,
1      IZLOCJ,IZLOCK)
C**
C**      THIS SUBROUTINE IS USED TO PLOT INITIAL, PARTIALLY CONVERGED
C**      OR CONVERGED SOLN. ISOLN = 1 INDICATES INITIAL GUESS
C**      ISOLN = 2 AND KKK = 0 INDICATES PARTIALLY CONVERGED SOLN.
C**      ISOLN = 2 AND KKK = 1 INDICATES CONVERGED SOLN.
C**
C**      GLOBAL COMMON STATEMENTS
C**
COMMON /BXXX/ Y(JMXLL,KMXLL),Z(JMXLL,KMXLL),Q(JMXLL),R(KMXLL),
1      X(IMXLL),Y1(IMXLL),Z1(IMXLL)
COMMON /AXXX/ ILIMIT,JLIMIT,KLIMIT,IMAX,JMAX,KMAX,IPRT1,IPRT2,
1      IPLT1,IPLT2,ITERMX,R1,R2,R3,I1,HE01(4),HE02(4)
C**
C**      LOCAL DIMENSION STATEMENTS
C**
DIMENSION YDUM(KMXLL),YDUM1(JMXLL),ZDUM(KMXLL),ZDUM1(JMXLL),
1      HED(4)

```

```

CORD1 485
CORD1 486
CORD1 487
CORD1 488
CORD1 489
CORD1 490
CORD1 491
CORD1 492
CORD1 493
CORD1 494
CORD1 495
CORD1 496
CORD1 497
CORD1 498
CORD1 499
CORD1 500
CORD1 501
CORD1 502
CORD1 503
CORD1 504
CORD1 505
CORD1 506
CORD1 507
CORD1 508
CORD1 509
CORD1 510
CORD1 511
CORD1 512
CORD1 513
CORD1 514
CORD1 515
CORD1 516
CORD1 517
CORD1 518
CORD1 519
CORD1 520
CORD1 521
CORD1 522
CORD1 523
CORD1 524
CORD1 525
CORD1 526
CORD1 527
CORD1 528

```

```

C**
C**      WRITE HEADINGS. TWO CARDS ARE READ IN THE
C**      MAIN PROGRAM WITH 40 COLUMNS INFORMATION ON EACH CARD
C**      WHENEVER IPLT1 OR IPLT2 = 1.
C**
      CALL SCRIBE(0.3,1.5,0.15,0.5,HED1,90.,40,9)
      CALL SCRIBE(0.55,1.5,0.15,0.5,HED2,90.,40,9)
C**
C**      PRINT HEADINGS FIRST
C**
      IF(ISOLN.EQ.2) GO TO 50
      HED(1) = 10H--- INITIA
      HED(2) = 10HL GUESS --
      HED(3) = 1H-
      CALL SCRIBE(0.70,3.0,0.1,0.5,HED,90.0,21,9)
      GO TO 100
C**
C**      PARTIALLY CONVERGED OR CONVERGED SOLN
C**
50 CONTINUE
      IF(KKK.EQ.1) GO TO 75
      HED(1) = 10H--- PARTIA
      HED(2) = 10HLLY CONVER
      HED(3) = 10HGEO SOLUTI
      HED(4) = 7HON ---
      CALL SCRIBE(0.70,3.0,0.1,0.5,HED,90.0,37,9)
      GO TO 100
75 CONTINUE
      HED(1) = 10H--- CONVER
      HED(2) = 10HGEO SOLUTI
      HED(3) = 6HON ---
      CALL SCRIBE(0.70,3.0,0.1,0.5,HED,90.0,26,9)
100 CONTINUE
C**
C**      WRITE ARRAY SIZES
C**
      ENCODE(40,1000,HED) JMAX,KMAX
      CALL SCRIBE(0.85,3.0,0.1,0.5,HED,90.0,27,9)
C**
C**      CALL NFRAME TO ADVANCE FRAME AFTER WRITING HEADINGS
C**
      CALL NFRAME
C**
C**      FIND MIN MAX VALUE FOR PLOTTING

```

```

CORD1 529
CORD1 530
CORD1 531
CORD1 532
CORD1 533
CORD1 534
CORD1 535
CORD1 536
CORD1 537
CORD1 538
CORD1 539
CORD1 540
CORD1 541
CORD1 542
CORD1 543
CORD1 544
CORD1 545
CORD1 546
CORD1 547
CORD1 548
CORD1 549
CORD1 550
CORD1 551
CORD1 552
CORD1 553
CORD1 554
CORD1 555
CORD1 556
CORD1 557
CORD1 558
CORD1 559
CORD1 560
CORD1 561
CORD1 562
CORD1 563
CORD1 564
CORD1 565
CORD1 566
CORD1 567
CORD1 568
CORD1 569
CORD1 570
CORD1 571
CORD1 572

```

```
C**
  YMIN = 10000.0
  ZMIN = 10000.0
  YMAX = -10000.0
  ZMAX = -10000.0
  DO 150 J = 1,JMAX
  DO 150 K = 1,KMAX
    IF(Y(J,K).LT.YMIN) YMIN = Y(J,K)
    IF(Y(J,K).GT.YMAX) YMAX = Y(J,K)
    IF(Z(J,K).LT.ZMIN) ZMIN = Z(J,K)
    IF(Z(J,K).GT.ZMAX) ZMAX = Z(J,K)
  150 CONTINUE
C**
C**      PLOT DATA. ZETA LINES FIRST
C**
  DO 210 J = 1,JMAX
  DO 200 K = 1,KMAX
    YDUM(K) = Y(J,K)
    ZDUM(K) = Z(J,K)
  200 CONTINUE
  CALL INFOPLT(0,KMAX,YDUM,1,ZDUM,1,YMIN,YMAX,ZMIN,ZMAX,
  1 1.0,0,HED,0,HED,0,5.0,5.0,0.0,2.0)
  210 CONTINUE
C**
C**      PLOT ETA LINES
C**
  KK = 0
  DO 250 K = 1,KMAX
    IF(K.EQ.KMAX) KK = 1
    DO 240 J = 1,JMAX
      YDUM1(J) = Y(J,K)
      ZDUM1(J) = Z(J,K)
    240 CONTINUE
    CALL INFOPLT(KK,JMAX,YDUM1,1,ZDUM1,1,YMIN,YMAX,ZMIN,ZMAX,
    1 1.0,0,HED,0,HED,0,5.0,5.0,0.0,2.0)
  250 CONTINUE
C**
C**      RETURN
C**
  1000 FORMAT(7HJMAX = ,I5,10H KMAX = ,I5)
C**
  END
```

```
CORD1 573
CORD1 574
CORD1 575
CORD1 576
CORD1 577
CORD1 578
CORD1 579
CORD1 580
CORD1 581
CORD1 582
CORD1 583
CORD1 584
CORD1 585
CORD1 586
CORD1 587
CORD1 588
CORD1 589
CORD1 590
CORD1 591
CORD1 592
CORD1 593
CORD1 594
CORD1 595
CORD1 596
CORD1 597
CORD1 598
CORD1 599
CORD1 600
CORD1 601
CORD1 602
CORD1 603
CORD1 604
CORD1 605
CORD1 606
CORD1 607
CORD1 608
CORD1 609
CORD1 610
CORD1 611
CORD1 612
CORD1 613
CORD1 614
```



B. Job Control Cards

A list of job control cards needed to run this program are included in the comment section of the main program COORDC.

C. Input Explanation

The instructions for input preparation are included in the comment section of the main program COORDC.

D. Sample Input

Sample input listing follows on the next page.

E. Sample Output

The sample output generated by the sample input of section D follows sample input.

PROGRAM NO. \_\_\_\_\_  
CODED BY \_\_\_\_\_  
DIVISION \_\_\_\_\_ SECTION \_\_\_\_\_

LANGLEY RESEARCH CENTER  
FORTRAN - DATA CODING FORM

DATE \_\_\_\_\_  
PAGE \_\_\_\_\_  
JOB ORDER \_\_\_\_\_

D. Sample Input

STATEMENT NUMBER	CONTINUATION	FORTRAN STATEMENT																																																																							
1	2	3	4	5	6	7	8	9	10	11	12	13	14	15	16	17	18	19	20	21	22	23	24	25	26	27	28	29	30	31	32	33	34	35	36	37	38	39	40	41	42	43	44	45	46	47	48	49	50	51	52	53	54	55	56	57	58	59	60	61	62	63	64	65									
		2	3				2	3				1				1				1				1					3	0	0													0	.	6			0	.	0	0	0	0	1		0	.															
	0	.	0	3	0	1	1	3	8		0	.	0	3	0	1	1	3	8																																																						
	0	.	0	3	3	6	7	3	4		0	.	0	2	6	7	2	2	8																																																						
	0	.	0	3	8	7	3	2	1		0	.	0	2	2	4	1	6	7																																																						
	0	.	0	4	6	4	8	6	7		0	.	0	1	6	8	0	4	8																																																						
	0	.	0	5	7	8	1	9	5		0	.	0	1	0	3	7	0	4																																																						
	0	.	0	7	3	3	3	4	9		0	.	0	0	4	1	3	3	3																																																						
	0	.	0	9	3	3	7	8	6		0	.	0	0	0	4	3	3	9																																																						
	0	.	1	1	8	0	7	2																																																																	
	0	.	1	4	7	3	3	6																																																																	
	0	.	1	8	0	9	1	7																																																																	
	0	.	2	1	8	4	1	9																																																																	
	0	.	2	5	9	3	2	5																																																																	
	0	.	3	0	3	0	2	7																																																																	
	0	.	3	4	8	8	5	6																																																																	
	0	.	3	9	6	1	0	2																																																																	
	0	.	4	4	4	0	5	0																																																																	
	0	.	4	9	2	0	0	1																																																																	
	0	.	5	3	9	3	0	4																																																																	
	0	.	5	8	5	3	8	0																																																																	
	0	.	6	2	9	7	4	4																																																																	
	0	.	6	7	2	0	4	4																																																																	
	0	.	7	1	2	0	9	4																																																																	
	0	.	7	5	0	0	0	0																																																																	
	0	.	0	3	0	1	1	3	8		0	.	0	3	0	1	1	3	8																																																						

DIVISION \_\_\_\_\_ SECTION \_\_\_\_\_

**FORTTRAN - DATA CODING FORM**

JOB ORDER\_\_\_\_\_

[illegible]

DATE\_\_\_\_\_

PAGE\_\_\_\_\_

JOB ORDER\_\_\_\_\_

[illegible]



# E. SAMPLE OUTPUT

\*\*\* INITIAL SOLUTION \*\*\*  
CORNER FLOW WITH FILLET  
COORDINATE SYSTEM. SIZE=30X23X23

JMAX = 23 KMAX = 23

J	(Y-Z ARRAY)	1	2	3	4	5	6	7	8	9	10
1	(Y-Z ARRAY)	.30114E-01	.30114E-01	.26723E-01	.33673E-01	.22417E-01	.38732E-01	.16805E-01	.46487E-01	.10370E-01	.37820E-01
2	(Y-Z ARRAY)	.41333E-02	.73335E-01	.43390E-03	.93379E-01	0.	.11807E+00	0.	.14734E+00	0.	.18092E+00
3	(Y-Z ARRAY)	0.	.21842E+00	0.	.25933E+00	0.	.30303E+00	0.	.34886E+00	0.	.39610E+00
4	(Y-Z ARRAY)	0.	.44405E+00	0.	.49200E+00	0.	.53930E+00	0.	.58538E+00	0.	.62974E+00
5	(Y-Z ARRAY)	0.	.67204E+00	0.	.71209E+00	0.	.75000E+00	0.	0.	0.	0.
6	(Y-Z ARRAY)	.33673E-01	.26723E-01	.30299E-01	.30299E-01	.26014E-01	.35382E-01	.20430E-01	.43173E-01	.14028E-01	.54559E-01
7	(Y-Z ARRAY)	.78214E-02	.70147E-01	.41403E-02	.90286E-01	.37085E-02	.11510E+00	.37085E-02	.14450E+00	.37085E-02	.17824E+00
8	(Y-Z ARRAY)	.37065E-02	.21592E+00	.37065E-02	.25701E+00	.37085E-02	.30092E+00	.37085E-02	.34697E+00	.37085E-02	.39443E+00
9	(Y-Z ARRAY)	.37085E-02	.44261E+00	.37065E-02	.49079E+00	.37085E-02	.53831E+00	.37085E-02	.58460E+00	.37085E-02	.62918E+00
10	(Y-Z ARRAY)	.37085E-02	.67168E+00	.37085E-02	.71192E+00	.37085E-02	.75000E+00	0.	0.	0.	0.
11	(Y-Z ARRAY)	.38732E-01	.22417E-01	.35382E-01	.26014E-01	.31127E-01	.31127E-01	.25582E-01	.38965E-01	.19225E-01	.50419E-01
12	(Y-Z ARRAY)	.13063E-01	.66100E-01	.94075E-02	.86358E-01	.89788E-02	.11132E+00	.89788E-02	.14089E+00	.89788E-02	.17483E+00
13	(Y-Z ARRAY)	.69788E-02	.21274E+00	.89788E-02	.25408E+00	.89788E-02	.29825E+00	.89788E-02	.34457E+00	.89788E-02	.39232E+00
14	(Y-Z ARRAY)	.89788E-02	.44078E+00	.89788E-02	.48924E+00	.89788E-02	.53705E+00	.89788E-02	.58362E+00	.89788E-02	.62846E+00
15	(Y-Z ARRAY)	.69788E-02	.67121E+00	.89788E-02	.71169E+00	.89788E-02	.75000E+00	0.	0.	0.	0.
16	(Y-Z ARRAY)	.46487E-01	.16805E-01	.43173E-01	.20430E-01	.38965E-01	.25582E-01	.33480E-01	.33480E-01	.27192E-01	.45023E-01
17	(Y-Z ARRAY)	.21097E-01	.60825E-01	.17482E-01	.81239E-01	.17058E-01	.10639E+00	.17058E-01	.13619E+00	.17058E-01	.17040E+00
18	(Y-Z ARRAY)	.17058E-01	.20859E+00	.17058E-01	.25025E+00	.17058E-01	.29476E+00	.17058E-01	.34144E+00	.17058E-01	.38956E+00
19	(Y-Z ARRAY)	.17058E-01	.43839E+00	.17058E-01	.48723E+00	.17058E-01	.53541E+00	.17058E-01	.58234E+00	.17058E-01	.62752E+00
20	(Y-Z ARRAY)	.17058E-01	.67060E+00	.17058E-01	.71139E+00	.17058E-01	.75000E+00	0.	0.	0.	0.
21	(Y-Z ARRAY)	.57820E-01	.10370E-01	.38836E-01	.14028E-01	.50419E-01	.19225E-01	.45023E-01	.27192E-01	.38836E-01	.38836E-01
22	(Y-Z ARRAY)	.32839E-01	.54777E-01	.29282E-01	.75370E-01	.28865E-01	.10074E+00	.28865E-01	.13081E+00	.28865E-01	.16531E+00
23	(Y-Z ARRAY)	.28865E-01	.20384E+00	.28865E-01	.24587E+00	.28865E-01	.29077E+00	.28865E-01	.33785E+00	.28865E-01	.38640E+00
24	(Y-Z ARRAY)	.28865E-01	.43566E+00	.28865E-01	.48493E+00	.28865E-01	.53353E+00	.28865E-01	.58087E+00	.28865E-01	.62645E+00
25	(Y-Z ARRAY)	.28865E-01	.66991E+00	.28865E-01	.71105E+00	.28865E-01	.75000E+00	0.	0.	0.	0.
26	(Y-Z ARRAY)	.73335E-01	.41333E-02	.70147E-01	.78214E-02	.66100E-01	.13063E-01	.60825E-01	.21097E-01	.54777E-01	.32839E-01
27	(Y-Z ARRAY)	.48914E-01	.48914E-01	.45437E-01	.69681E-01	.45029E-01	.95266E-01	.45029E-01	.12559E+00	.45029E-01	.16038E+00
28	(Y-Z ARRAY)	.45029E-01	.19923E+00	.45029E-01	.24162E+00	.45029E-01	.28690E+00	.45029E-01	.33430E+00	.45029E-01	.38333E+00
29	(Y-Z ARRAY)	.45029E-01	.43301E+00	.45029E-01	.48269E+00	.45029E-01	.53170E+00	.45029E-01	.57944E+00	.45029E-01	.62540E+00
30	(Y-Z ARRAY)	.45029E-01	.66923E+00	.45029E-01	.71073E+00	.45029E-01	.75000E+00	0.	0.	0.	0.

35

J = 7	(Y-Z ARRAY)								
.93379E-01	.43390E-03	.90286E-01	.41403E-02	.86358E-01	.94075E-02	.81239E-01	.17482E-01	.75370E-01	.29282E-01
.69681E-01	.45437E-01	.66307E-01	.66307E-01	.65911E-01	.92018E-01	.65911E-01	.12249E+00	.65911E-01	.15745E+00
.65911E-01	.19650E+00	.65911E-01	.23910E+00	.65911E-01	.28460E+00	.65911E-01	.33232E+00	.65911E-01	.38151E+00
.65911E-01	.43144E+00	.65911E-01	.48136E+00	.65911E-01	.53062E+00	.65911E-01	.57859E+00	.65911E-01	.62479E+00
.65911E-01	.66883E+00	.65911E-01	.71053E+00	.65911E-01	.75000E+00				
J = 8	(Y-Z ARRAY)								
.11807E+00	0.	.11510E+00	.37085E-02	.11132E+00	.89788E-02	.10639E+00	.17058E-01	.10074E+00	.28865E-01
.95266E-01	.45029E-01	.92018E-01	.65911E-01	.91638E-01	.91638E-01	.91638E-01	.12213E+00	.91638E-01	.15711E+00
.91638E-01	.19618E+00	.91638E-01	.23880E+00	.91638E-01	.28433E+00	.91638E-01	.33208E+00	.91638E-01	.38130E+00
.91638E-01	.43125E+00	.91638E-01	.48121E+00	.91638E-01	.53049E+00	.91638E-01	.57849E+00	.91638E-01	.62471E+00
.91638E-01	.66878E+00	.91638E-01	.71051E+00	.91638E-01	.75000E+00				
J = 9	(Y-Z ARRAY)								
.14734E+00	0.	.14450E+00	.37085E-02	.14089E+00	.89788E-02	.13619E+00	.17058E-01	.13081E+00	.28865E-01
.12559E+00	.45029E-01	.12249E+00	.65911E-01	.12213E+00	.91638E-01	.12213E+00	.12213E+00	.12213E+00	.15711E+00
.12213E+00	.19618E+00	.12213E+00	.23880E+00	.12213E+00	.28433E+00	.12213E+00	.33208E+00	.12213E+00	.38130E+00
.12213E+00	.43125E+00	.12213E+00	.48121E+00	.12213E+00	.53049E+00	.12213E+00	.57849E+00	.12213E+00	.62471E+00
.12213E+00	.66878E+00	.12213E+00	.71051E+00	.12213E+00	.75000E+00				
J = 10	(Y-Z ARRAY)								
.18092E+00	0.	.17824E+00	.37085E-02	.17483E+00	.89788E-02	.17040E+00	.17058E-01	.16531E+00	.28865E-01
.16038E+00	.45029E-01	.15745E+00	.65911E-01	.15711E+00	.91638E-01	.15711E+00	.12213E+00	.15711E+00	.15711E+00
.15711E+00	.19618E+00	.15711E+00	.23880E+00	.15711E+00	.28433E+00	.15711E+00	.33208E+00	.15711E+00	.38130E+00
.15711E+00	.43125E+00	.15711E+00	.48121E+00	.15711E+00	.53049E+00	.15711E+00	.57849E+00	.15711E+00	.62471E+00
.15711E+00	.66878E+00	.15711E+00	.71051E+00	.15711E+00	.75000E+00				
J = 11	(Y-Z ARRAY)								
.21842E+00	0.	.21592E+00	.37085E-02	.21274E+00	.89788E-02	.20859E+00	.17058E-01	.20384E+00	.28865E-01
.19923E+00	.45029E-01	.19650E+00	.65911E-01	.19618E+00	.91638E-01	.19618E+00	.12213E+00	.19618E+00	.15711E+00
.19618E+00	.19618E+00	.19618E+00	.23880E+00	.19618E+00	.28433E+00	.19618E+00	.33208E+00	.19618E+00	.38130E+00
.19618E+00	.43125E+00	.19618E+00	.48121E+00	.19618E+00	.53049E+00	.19618E+00	.57849E+00	.19618E+00	.62471E+00
.19618E+00	.66878E+00	.19618E+00	.71051E+00	.19618E+00	.75000E+00				
J = 12	(Y-Z ARRAY)								
.25933E+00	0.	.25701E+00	.37085E-02	.25408E+00	.89788E-02	.25025E+00	.17058E-01	.24587E+00	.28865E-01
.24162E+00	.45029E-01	.23910E+00	.65911E-01	.23880E+00	.91638E-01	.23880E+00	.12213E+00	.23880E+00	.15711E+00
.23880E+00	.19618E+00	.23880E+00	.23880E+00	.23880E+00	.28433E+00	.23880E+00	.33208E+00	.23880E+00	.38130E+00
.23880E+00	.43125E+00	.23880E+00	.48121E+00	.23880E+00	.53049E+00	.23880E+00	.57849E+00	.23880E+00	.62471E+00
.23880E+00	.66878E+00	.23880E+00	.71051E+00	.23880E+00	.75000E+00				
J = 13	(Y-Z ARRAY)								
.30303E+00	0.	.30092E+00	.37085E-02	.29825E+00	.89788E-02	.29476E+00	.17058E-01	.29077E+00	.28865E-01
.26690E+00	.45029E-01	.28460E+00	.65911E-01	.28433E+00	.91638E-01	.28433E+00	.12213E+00	.28433E+00	.15711E+00
.28433E+00	.19618E+00	.28433E+00	.23880E+00	.28433E+00	.28433E+00	.28433E+00	.33208E+00	.28433E+00	.38130E+00
.28433E+00	.43125E+00	.28433E+00	.48121E+00	.28433E+00	.53049E+00	.28433E+00	.57849E+00	.28433E+00	.62471E+00
.28433E+00	.66878E+00	.28433E+00	.71051E+00	.28433E+00	.75000E+00				

J = 14 (Y-Z ARRAY)

.34886E+00	0.	.34697E+00	.37085E-02	.34457E+00	.8976E-02	.34144E+00	.17058E-01	.33705E+00	.28865E-01
.33438E+00	.45029E-01	.33232E+00	.65911E-01	.33208E+00	.91638E-01	.33208E+00	.12213E+00	.33208E+00	.15711E+00
.33208E+00	.19618E+00	.33208E+00	.23880E+00	.33208E+00	.28433E+00	.33208E+00	.33208E+00	.33208E+00	.38130E+00
.33208E+00	.43125E+00	.33208E+00	.48121E+00	.33208E+00	.53049E+00	.33208E+00	.57849E+00	.33208E+00	.62471E+00
.33208E+00	.66878E+00	.33208E+00	.71051E+00	.33208E+00	.75000E+00				

J = 15 (Y-Z ARRAY)

.39610E+00	0.	.39443E+00	.37085E-02	.39232E+00	.89788E-02	.38956E+00	.17058E-01	.38640E+00	.28865E-01
.38333E+00	.45029E-01	.38151E+00	.65911E-01	.38130E+00	.91638E-01	.38130E+00	.12213E+00	.38130E+00	.15711E+00
.38130E+00	.19618E+00	.38130E+00	.23880E+00	.38130E+00	.28433E+00	.38130E+00	.33208E+00	.38130E+00	.38130E+00
.38130E+00	.43125E+00	.38130E+00	.48121E+00	.38130E+00	.53049E+00	.38130E+00	.57849E+00	.38130E+00	.62471E+00
.38130E+00	.66878E+00	.38130E+00	.71051E+00	.38130E+00	.75000E+00				

J = 16 (Y-Z ARRAY)

.44405E+00	0.	.44261E+00	.37085E-02	.44078E+00	.89788E-02	.43839E+00	.17058E-01	.43566E+00	.28865E-01
.43301E+00	.45029E-01	.43144E+00	.65911E-01	.43125E+00	.91638E-01	.43125E+00	.12213E+00	.43125E+00	.15711E+00
.43125E+00	.19618E+00	.43125E+00	.23880E+00	.43125E+00	.28433E+00	.43125E+00	.33208E+00	.43125E+00	.38130E+00
.43125E+00	.43125E+00	.43125E+00	.48121E+00	.43125E+00	.53049E+00	.43125E+00	.57849E+00	.43125E+00	.62471E+00
.43125E+00	.66878E+00	.43125E+00	.71051E+00	.43125E+00	.75000E+00				

J = 17 (Y-Z ARRAY)

.49200E+00	0.	.49079E+00	.37085E-02	.48924E+00	.89788E-02	.48723E+00	.17058E-01	.48493E+00	.28865E-01
.48269E+00	.45029E-01	.48136E+00	.65911E-01	.48121E+00	.91638E-01	.48121E+00	.12213E+00	.48121E+00	.15711E+00
.48121E+00	.19618E+00	.48121E+00	.23880E+00	.48121E+00	.28433E+00	.48121E+00	.33208E+00	.48121E+00	.38130E+00
.48121E+00	.43125E+00	.48121E+00	.48121E+00	.48121E+00	.53049E+00	.48121E+00	.57849E+00	.48121E+00	.62471E+00
.48121E+00	.66878E+00	.48121E+00	.71051E+00	.48121E+00	.75000E+00				

J = 18 (Y-Z ARRAY)

.53930E+00	0.	.53831E+00	.37085E-02	.53705E+00	.89788E-02	.53541E+00	.17058E-01	.53353E+00	.28865E-01
.53170E+00	.45029E-01	.53062E+00	.65911E-01	.53049E+00	.91638E-01	.53049E+00	.12213E+00	.53049E+00	.15711E+00
.53049E+00	.19618E+00	.53049E+00	.23880E+00	.53049E+00	.28433E+00	.53049E+00	.33208E+00	.53049E+00	.38130E+00
.53049E+00	.43125E+00	.53049E+00	.48121E+00	.53049E+00	.53049E+00	.53049E+00	.57849E+00	.53049E+00	.62471E+00
.53049E+00	.66878E+00	.53049E+00	.71051E+00	.53049E+00	.75000E+00				

J = 19 (Y-Z ARRAY)

.58538E+00	0.	.58460E+00	.37085E-02	.58362E+00	.89788E-02	.58234E+00	.17058E-01	.58087E+00	.28865E-01
.57944E+00	.45029E-01	.57859E+00	.65911E-01	.57849E+00	.91638E-01	.57849E+00	.12213E+00	.57849E+00	.15711E+00
.57849E+00	.19618E+00	.57849E+00	.23880E+00	.57849E+00	.28433E+00	.57849E+00	.33208E+00	.57849E+00	.38130E+00
.57849E+00	.43125E+00	.57849E+00	.48121E+00	.57849E+00	.53049E+00	.57849E+00	.57849E+00	.57849E+00	.62471E+00
.57849E+00	.66878E+00	.57849E+00	.71051E+00	.57849E+00	.75000E+00				

J = 20 (Y-Z ARRAY)

.62974E+00	0.	.62918E+00	.37085E-02	.62846E+00	.89788E-02	.62752E+00	.17058E-01	.62645E+00	.28865E-01
.62540E+00	.45029E-01	.62479E+00	.65911E-01	.62471E+00	.91638E-01	.62471E+00	.12213E+00	.62471E+00	.15711E+00
.62471E+00	.19618E+00	.62471E+00	.23880E+00	.62471E+00	.28433E+00	.62471E+00	.33208E+00	.62471E+00	.38130E+00
.62471E+00	.43125E+00	.62471E+00	.48121E+00	.62471E+00	.53049E+00	.62471E+00	.57849E+00	.62471E+00	.62471E+00
.62471E+00	.66878E+00	.62471E+00	.71051E+00	.62471E+00	.75000E+00				



J = 21 (Y-Z ARRAY)

.67204E+00	0.	.67168E+00	.37085E-02	.67121E+00	.89788E-02	.67060E+00	.17058E-01	.66991E+00	.28865E-01
.66923E+00	.45029E-01	.66883E+00	.65911E-01	.66878E+00	.91638E-01	.66878E+00	.12213E+00	.66878E+00	.15711E+00
.66878E+00	.19618E+00	.66878E+00	.23880E+00	.66878E+00	.28433E+00	.66878E+00	.33208E+00	.66878E+00	.38130E+00
.66878E+00	.43125E+00	.66878E+00	.48121E+00	.66878E+00	.53049E+00	.66878E+00	.57849E+00	.66878E+00	.62471E+00
.66878E+00	.66878E+00	.66878E+00	.71051E+00	.66878E+00	.75000E+00				

J = 22 (Y-Z ARRAY)

.71209E+00	0.	.71192E+00	.37085E-02	.71169E+00	.89788E-02	.71139E+00	.17058E-01	.71105E+00	.28865E-01
.71073E+00	.45029E-01	.71053E+00	.65911E-01	.71051E+00	.91638E-01	.71051E+00	.12213E+00	.71051E+00	.15711E+00
.71051E+00	.19618E+00	.71051E+00	.23880E+00	.71051E+00	.28433E+00	.71051E+00	.33208E+00	.71051E+00	.38130E+00
.71051E+00	.43125E+00	.71051E+00	.48121E+00	.71051E+00	.53049E+00	.71051E+00	.57849E+00	.71051E+00	.62471E+00
.71051E+00	.66878E+00	.71051E+00	.71051E+00	.71051E+00	.75000E+00				

J = 23 (Y-Z ARRAY)

.75000E+00	0.	.75000E+00	.37085E-02	.75000E+00	.89788E-02	.75000E+00	.17058E-01	.75000E+00	.28865E-01
.75000E+00	.45029E-01	.75000E+00	.65911E-01	.75000E+00	.91638E-01	.75000E+00	.12213E+00	.75000E+00	.15711E+00
.75000E+00	.19618E+00	.75000E+00	.23880E+00	.75000E+00	.28433E+00	.75000E+00	.33208E+00	.75000E+00	.38130E+00
.75000E+00	.43125E+00	.75000E+00	.48121E+00	.75000E+00	.53049E+00	.75000E+00	.57849E+00	.75000E+00	.62471E+00
.75000E+00	.66878E+00	.75000E+00	.71051E+00	.75000E+00	.75000E+00				

J=1,K=1,X=1,IMAX (X,Y,Z ARRAY)

0.	.30114E-01	.30114E-01	.68190E-02	.30114E-01	.30114E-01	.13640E-01	.30114E-01	.30114E-01
.20480E-01	.30114E-01	.30114E-01	.27370E-01	.30114E-01	.30114E-01	.34460E-01	.30114E-01	.30114E-01
.42120E-01	.30114E-01	.30114E-01	.51190E-01	.30114E-01	.30114E-01	.63230E-01	.30114E-01	.30114E-01
.80520E-01	.30114E-01	.30114E-01	.10560E+00	.30114E-01	.30114E-01	.14120E+00	.30114E-01	.30114E-01
.17660E+00	.30114E-01	.30114E-01	.21200E+00	.30114E-01	.30114E-01	.24740E+00	.30114E-01	.30114E-01
.28280E+00	.30114E-01	.30114E-01	.31820E+00	.30114E-01	.30114E-01	.35360E+00	.30114E-01	.30114E-01
.38900E+00	.30114E-01	.30114E-01	.42440E+00	.30114E-01	.30114E-01	.45980E+00	.30114E-01	.30114E-01
.49520E+00	.30114E-01	.30114E-01	.53060E+00	.30114E-01	.30114E-01	.56600E+00	.30114E-01	.30114E-01
.60140E+00	.30114E-01	.30114E-01	.63680E+00	.30114E-01	.30114E-01	.67220E+00	.30114E-01	.30114E-01
.70760E+00	.30114E-01	.30114E-01	.74300E+00	.30114E-01	.30114E-01	.77840E+00	.30114E-01	.30114E-01

ITER NO., IYLOCJ, IYLOCK, YERRMX, IZLOCJ, IZLOCK, ZERRMX = 50 13 9 .716194E-04 9 13 .715067E-04

\*\*\* PARTIALLY CONVERGED SOLUTION \*\*\*  
 CORNER FLOW WITH FILLET  
 COORDINATE SYSTEM. SIZE=30X23X23

JMAX = 23 KMAX = 23  
 MAX ITERATIONS PERFORMED = 50  
 MAX Y-ERROR = .716194E-04 AT LOC. J,K = 13, 9  
 MAX Z-ERROR = .715067E-04 AT LOC. J,K = 9, 13

J = 1	(Y-Z ARRAY)									
.30114E-01	.30114E-01	.26723E-01	.33673E-01	.22417E-01	.38732E-01	.16805E-01	.46487E-01	.10370E-01	.57820E-01	
.41333E-02	.73335E-01	.43390E-03	.93379E-01	0.	.11807E+00	0.	.14734E+00	0.	.18092E+00	
0.	.21842E+00	0.	.25933E+00	0.	.30303E+00	0.	.34886E+00	0.	.39610E+00	
0.	.44405E+00	0.	.49200E+00	0.	.53930E+00	0.	.58538E+00	0.	.62974E+00	
0.	.67204E+00	0.	.71209E+00	0.	.75000E+00					
J = 2	(Y-Z ARRAY)									
.33673E-01	.26723E-01	.31702E-01	.31701E-01	.27769E-01	.37616E-01	.21884E-01	.45740E-01	.14952E-01	.57186E-01	
.83199E-02	.72725E-01	.42756E-02	.92742E-01	.36043E-02	.11739E+00	.35675E-02	.14666E+00	.35631E-02	.18028E+00	
.35618E-02	.21764E+00	.35612E-02	.25881E+00	.35609E-02	.30256E+00	.35608E-02	.34845E+00	.35607E-02	.39575E+00	
.35607E-02	.44375E+00	.35607E-02	.49175E+00	.35607E-02	.53911E+00	.35607E-02	.58523E+00	.35607E-02	.62964E+00	
.35607E-02	.67198E+00	.35607E-02	.71206E+00	.35607E-02	.75000E+00					
J = 3	(Y-Z ARRAY)									
.38732E-01	.22417E-01	.37617E-01	.27767E-01	.34763E-01	.34759E-01	.29291E-01	.43940E-01	.21859E-01	.55983E-01	
.14507E-01	.71740E-01	.98591E-02	.91793E-01	.87786E-02	.11642E+00	.86534E-02	.14572E+00	.86337E-02	.17941E+00	
.86275E-02	.21705E+00	.86249E-02	.25809E+00	.86237E-02	.30193E+00	.86231E-02	.34790E+00	.86228E-02	.39527E+00	
.86227E-02	.44335E+00	.86227E-02	.49142E+00	.86227E-02	.53884E+00	.86227E-02	.58503E+00	.86228E-02	.62950E+00	
.86228E-02	.67189E+00	.86228E-02	.71202E+00	.86228E-02	.75000E+00					
J = 4	(Y-Z ARRAY)									
.46487E-01	.16805E-01	.45741E-01	.21882E-01	.43945E-01	.29285E-01	.39751E-01	.39741E-01	.32753E-01	.53135E-01	
.24717E-01	.69736E-01	.18930E-01	.90143E-01	.16948E-01	.11490E+00	.16537E-01	.14430E+00	.16445E-01	.17810E+00	
.16415E-01	.21587E+00	.16402E-01	.25705E+00	.16396E-01	.30101E+00	.16394E-01	.34709E+00	.16392E-01	.39458E+00	
.16392E-01	.44276E+00	.16391E-01	.49094E+00	.16391E-01	.53846E+00	.16392E-01	.58474E+00	.16392E-01	.62929E+00	
.16392E-01	.67177E+00	.16392E-01	.71197E+00	.16392E-01	.75000E+00					
J = 5	(Y-Z ARRAY)									
.57820E-01	.10370E-01	.57187E-01	.14951E-01	.55987E-01	.21854E-01	.53145E-01	.32742E-01	.47573E-01	.47556E-01	
.39878E-01	.65704E-01	.32993E-01	.87178E-01	.29490E-01	.11250E+00	.28340E-01	.14220E+00	.27993E-01	.17625E+00	
.27870E-01	.21422E+00	.27818E-01	.25559E+00	.27794E-01	.29974E+00	.27783E-01	.34599E+00	.27777E-01	.39364E+00	
.27774E-01	.44197E+00	.27774E-01	.49029E+00	.27773E-01	.53795E+00	.27774E-01	.58435E+00	.27774E-01	.62902E+00	
.27775E-01	.67160E+00	.27775E-01	.71189E+00	.27775E-01	.75000E+00					
J = 6	(Y-Z ARRAY)									
.73335E-01	.41333E-02	.72726E-01	.83196E-02	.71742E-01	.14506E-01	.69744E-01	.24710E-01	.65721E-01	.39862E-01	
.59358E-01	.59335E-01	.52369E-01	.82352E-01	.47429E-01	.10885E+00	.45056E-01	.13926E+00	.44112E-01	.17374E+00	

.43733E-01	.21205E+00	.43567E-01	.25370E+00	.43490E-01	.29810E+00	.43452E-01	.34458E+00	.43433E-01	.39243E+00
.43425E-01	.44097E+00	.43421E-01	.48947E+00	.43420E-01	.53730E+00	.43421E-01	.58387E+00	.43423E-01	.62869E+00
.43424E-01	.67139E+00	.43425E-01	.71179E+00	.43425E-01	.75000E+00				

J = 7 (Y-Z ARRAY)

.93379E-01	.43390E-03	.92742E-01	.42756E-02	.91794E-01	.98587E-02	.90148E-01	.18928E-01	.87190E-01	.32983E-01
.82373E-01	.52350E-01	.76281E-01	.76255E-01	.70797E-01	.10399E+00	.67247E-01	.13540E+00	.65414E-01	.17057E+00
.64547E-01	.20937E+00	.64137E-01	.25141E+00	.63936E-01	.29612E+00	.63836E-01	.34289E+00	.63787E-01	.39101E+00
.63763E-01	.43979E+00	.63753E-01	.48852E+00	.63750E-01	.53656E+00	.63751E-01	.58332E+00	.63755E-01	.62830E+00
.63758E-01	.67116E+00	.63760E-01	.71169E+00	.63760E-01	.75000E+00				

J = 8 (Y-Z ARRAY)

.11807E+00	0.	.11739E+00	.36043E-02	.11642E+00	.87785E-02	.11490E+00	.16947E-01	.11251E+00	.29486E-01
.10387E+00	.47416E-01	.10401E+00	.70775E-01	.98893E-01	.98866E-01	.94763E-01	.13103E+00	.92096E-01	.16692E+00
.90595E-01	.20630E+00	.89799E-01	.24879E+00	.89384E-01	.29390E+00	.89168E-01	.34100E+00	.89058E-01	.38942E+00
.89004E-01	.43848E+00	.88979E-01	.48746E+00	.88972E-01	.53574E+00	.88973E-01	.58271E+00	.88978E-01	.62788E+00
.88984E-01	.67090E+00	.88989E-01	.71157E+00	.88989E-01	.75000E+00				

J = 9 (Y-Z ARRAY)

.14734E+00	0.	.14666E+00	.35674E-02	.14572E+00	.86532E-02	.14430E+00	.16536E-01	.14221E+00	.28337E-01
.13927E+00	.45049E-01	.13542E+00	.67232E-01	.13105E+00	.94741E-01	.12698E+00	.12696E+00	.12386E+00	.16324E+00
.12179E+00	.20309E+00	.12056E+00	.24604E+00	.11986E+00	.29154E+00	.11947E+00	.33900E+00	.11926E+00	.38776E+00
.11916E+00	.43711E+00	.11911E+00	.48637E+00	.11909E+00	.53489E+00	.11909E+00	.58209E+00	.11910E+00	.62746E+00
.11911E+00	.67064E+00	.11911E+00	.71145E+00	.11911E+00	.75000E+00				

J = 10 (Y-Z ARRAY)

.18092E+00	0.	.18028E+00	.35631E-02	.17941E+00	.86336E-02	.17810E+00	.16444E-01	.17624E+00	.27991E-01
.17374E+00	.44107E-01	.17058E+00	.65404E-01	.16694E+00	.92079E-01	.16327E+00	.12384E+00	.16009E+00	.16007E+00
.15771E+00	.20012E+00	.15611E+00	.24339E+00	.15512E+00	.28924E+00	.15454E+00	.33704E+00	.15421E+00	.38611E+00
.15404E+00	.43576E+00	.15395E+00	.48530E+00	.15392E+00	.53407E+00	.15391E+00	.58148E+00	.15392E+00	.62704E+00
.15393E+00	.67039E+00	.15394E+00	.71134E+00	.15394E+00	.75000E+00				

J = 11 (Y-Z ARRAY)

.21842E+00	0.	.21784E+00	.35617E-02	.21704E+00	.86274E-02	.21587E+00	.16414E-01	.21422E+00	.27869E-01
.21205E+00	.43730E-01	.20938E+00	.64541E-01	.20631E+00	.90583E-01	.20311E+00	.12178E+00	.20014E+00	.15769E+00
.19771E+00	.19769E+00	.19592E+00	.24108E+00	.19471E+00	.28717E+00	.19396E+00	.33524E+00	.19351E+00	.38459E+00
.19326E+00	.43452E+00	.19313E+00	.48431E+00	.19307E+00	.53331E+00	.19306E+00	.58093E+00	.19307E+00	.62667E+00
.19306E+00	.67016E+00	.19309E+00	.71123E+00	.19309E+00	.75000E+00				

J = 12 (Y-Z ARRAY)

.25933E+00	0.	.25880E+00	.35612E-02	.25809E+00	.86249E-02	.25704E+00	.16402E-01	.25559E+00	.27817E-01
.25370E+00	.43566E-01	.25140E+00	.64133E-01	.24880E+00	.89791E-01	.24604E+00	.12055E+00	.24340E+00	.15610E+00
.24110E+00	.19590E+00	.23928E+00	.23927E+00	.23798E+00	.28546E+00	.23711E+00	.33372E+00	.23657E+00	.38329E+00
.23626E+00	.43344E+00	.23609E+00	.48345E+00	.23601E+00	.53265E+00	.23599E+00	.58045E+00	.23599E+00	.62634E+00
.23600E+00	.66997E+00	.23601E+00	.71114E+00	.23601E+00	.75000E+00				

J = 13 (Y-Z ARRAY)

.30303E+00	0.	.30256E+00	.35609E-02	.30193E+00	.86237E-02	.30101E+00	.16396E-01	.29973E+00	.27794E-01
.29805E+00	.43489E-01	.29612E+00	.63934E-01	.29389E+00	.89379E-01	.29154E+00	.11985E+00	.28924E+00	.15511E+00

.28717E+00	.19470E+00	.28547E+00	.23797E+00	.28418E+00	.28418E+00	.28328E+00	.33253E+00	.28270E+00	.38225E+00
.28234E+00	.43257E+00	.28214E+00	.48275E+00	.28205E+00	.53212E+00	.29201E+00	.58006E+00	.28201E+00	.62608E+00
.28202E+00	.66981E+00	.28202E+00	.71107E+00	.28202E+00	.75000E+00				

J = 14 (Y-Z ARRAY)

.34886E+00	0.	.34845E+00	.35608E-02	.34789E+00	.86231E-02	.34709E+00	.16394E-01	.34598E+00	.27782E-01
.34457E+00	.43451E-01	.34288E+00	.63835E-01	.34099E+00	.89166E-01	.33900E+00	.11947E+00	.33704E+00	.15453E+00
.33525E+00	.19395E+00	.33373E+00	.23711E+00	.33254E+00	.28328E+00	.33168E+00	.33167E+00	.33109E+00	.38148E+00
.33073E+00	.43191E+00	.33052E+00	.48222E+00	.33041E+00	.53171E+00	.33036E+00	.57976E+00	.33035E+00	.62588E+00
.33036E+00	.66969E+00	.33036E+00	.71101E+00	.33036E+00	.75000E+00				

J = 15 (Y-Z ARRAY)

.39610E+00	0.	.39575E+00	.35607E-02	.39527E+00	.86228E-02	.39458E+00	.16392E-01	.39363E+00	.27777E-01
.39243E+00	.43433E-01	.39101E+00	.63786E-01	.38942E+00	.89057E-01	.38775E+00	.11926E+00	.38611E+00	.15421E+00
.38460E+00	.19350E+00	.38329E+00	.23657E+00	.38225E+00	.28269E+00	.38148E+00	.33109E+00	.38095E+00	.38094E+00
.38060E+00	.43145E+00	.38039E+00	.48184E+00	.38028E+00	.53141E+00	.38023E+00	.57955E+00	.38021E+00	.62573E+00
.38021E+00	.66960E+00	.38021E+00	.71097E+00	.38021E+00	.75000E+00				

J = 16 (Y-Z ARRAY)

.44405E+00	0.	.44375E+00	.35607E-02	.44334E+00	.86227E-02	.44276E+00	.16392E-01	.44197E+00	.27775E-01
.44096E+00	.43425E-01	.43978E+00	.63763E-01	.43847E+00	.89003E-01	.43710E+00	.11916E+00	.43576E+00	.15404E+00
.43452E+00	.19326E+00	.43344E+00	.23626E+00	.43257E+00	.28234E+00	.43191E+00	.33073E+00	.43145E+00	.38060E+00
.43114E+00	.43114E+00	.43096E+00	.48158E+00	.43085E+00	.53121E+00	.43080E+00	.57940E+00	.43077E+00	.62563E+00
.43077E+00	.66954E+00	.43077E+00	.71095E+00	.43077E+00	.75000E+00				

J = 17 (Y-Z ARRAY)

.49200E+00	0.	.49175E+00	.35607E-02	.49142E+00	.86227E-02	.49094E+00	.16391E-01	.49029E+00	.27774E-01
.48947E+00	.43421E-01	.48851E+00	.63753E-01	.48746E+00	.88980E-01	.48637E+00	.11911E+00	.48529E+00	.15395E+00
.48431E+00	.19313E+00	.48345E+00	.23609E+00	.48275E+00	.28214E+00	.48222E+00	.33057E+00	.48184E+00	.38039E+00
.48199E+00	.43096E+00	.48143E+00	.48142E+00	.48133E+00	.53108E+00	.48128E+00	.57930E+00	.48126E+00	.62556E+00
.48125E+00	.66950E+00	.48125E+00	.71093E+00	.48125E+00	.75000E+00				

J = 18 (Y-Z ARRAY)

.53930E+00	0.	.53911E+00	.35607E-02	.53884E+00	.86227E-02	.53846E+00	.16391E-01	.53794E+00	.27774E-01
.53730E+00	.43421E-01	.53655E+00	.63750E-01	.53573E+00	.88972E-01	.53489E+00	.11909E+00	.53406E+00	.15392E+00
.53331E+00	.19307E+00	.53265E+00	.23601E+00	.53212E+00	.28205E+00	.53171E+00	.33041E+00	.53141E+00	.38028E+00
.53121E+00	.43085E+00	.53108E+00	.48133E+00	.53101E+00	.53101E+00	.53096E+00	.57924E+00	.53094E+00	.62552E+00
.53093E+00	.66947E+00	.53093E+00	.71092E+00	.53093E+00	.75000E+00				

J = 19 (Y-Z ARRAY)

.58538E+00	0.	.58523E+00	.35607E-02	.58503E+00	.86227E-02	.58474E+00	.16392E-01	.58435E+00	.27774E-01
.58347E+00	.43421E-01	.58331E+00	.63752E-01	.58271E+00	.88973E-01	.58208E+00	.11909E+00	.58148E+00	.15391E+00
.58093E+00	.19306E+00	.58045E+00	.23599E+00	.58006E+00	.28201E+00	.57976E+00	.33036E+00	.57955E+00	.38023E+00
.57940E+00	.43080E+00	.57930E+00	.48128E+00	.57924E+00	.53096E+00	.57921E+00	.57921E+00	.57919E+00	.62550E+00
.57918E+00	.66946E+00	.57917E+00	.71091E+00	.57917E+00	.75000E+00				

J = 20 (Y-Z ARRAY)

.62974E+00	0.	.62964E+00	.35607E-02	.62950E+00	.86228E-02	.62929E+00	.16392E-01	.62902E+00	.27774E-01
.62669E+00	.42423E-01	.62930E+00	.63755E-01	.62788E+00	.88978E-01	.62745E+00	.11910E+00	.62704E+00	.15392E+00

.62666E+00	.19307E+00	.62634E+00	.23599E+00	.62608E+00	.28201E+00	.62588E+00	.33035E+00	.62573E+00	.38021E+00
.62563E+00	.43077E+00	.62556E+00	.48126E+00	.62552E+00	.53094E+00	.62550E+00	.57919E+00	.62548E+00	.62548E+00
.62547E+00	.66945E+00	.62547E+00	.71090E+00	.62547E+00	.75000E+00				
J = 21	(Y-Z ARRAY)								
.67204E+00	0.	.67198E+00	.35607E-02	.67189E+00	.86228E-02	.67177E+00	.16392E-01	.67160E+00	.27775E-01
.67139E+00	.43424E-01	.67116E+00	.63758E-01	.67090E+00	.88985E-01	.67064E+00	.11911E+00	.67039E+00	.15393E+00
.67016E+00	.19308E+00	.66997E+00	.23600E+00	.66981E+00	.28202E+00	.66969E+00	.33036E+00	.66960E+00	.38021E+00
.66954E+00	.43077E+00	.66950E+00	.48125E+00	.66947E+00	.53093E+00	.66946E+00	.57918E+00	.66945E+00	.62547E+00
.66944E+00	.66944E+00	.66944E+00	.71090E+00	.66944E+00	.75000E+00				
J = 22	(Y-Z ARRAY)								
.71209E+00	0.	.71206E+00	.35607E-02	.71202E+00	.86228E-02	.71197E+00	.16392E-01	.71189E+00	.27775E-01
.71179E+00	.43425E-01	.71169E+00	.63760E-01	.71157E+00	.88989E-01	.71145E+00	.11911E+00	.71134E+00	.15394E+00
.71123E+00	.19309E+00	.71114E+00	.23601E+00	.71107E+00	.28203E+00	.71101E+00	.33036E+00	.71097E+00	.38021E+00
.71095E+00	.43077E+00	.71093E+00	.48125E+00	.71092E+00	.53093E+00	.71091E+00	.57917E+00	.71090E+00	.62547E+00
.71090E+00	.66944E+00	.71090E+00	.71090E+00	.71090E+00	.75000E+00				
J = 23	(Y-Z ARRAY)								
.75000E+00	0.	.75000E+00	.35607E-02	.75000E+00	.86228E-02	.75000E+00	.16392E-01	.75000E+00	.27775E-01
.75000E+00	.43425E-01	.75000E+00	.63760E-01	.75000E+00	.88989E-01	.75000E+00	.11911E+00	.75000E+00	.15394E+00
.75000E+00	.19309E+00	.75000E+00	.23601E+00	.75000E+00	.28203E+00	.75000E+00	.33036E+00	.75000E+00	.38021E+00
.75000E+00	.43077E+00	.75000E+00	.48125E+00	.75000E+00	.53093E+00	.75000E+00	.57917E+00	.75000E+00	.62547E+00
.75000E+00	.66944E+00	.75000E+00	.71090E+00	.75000E+00	.75000E+00				
J=1,K=1,X=1,IMAX	(X,Y,Z ARRAY)								
0.	.30114E-01	.30114E-01	.68190E-02	.30114E-01	.30114E-01	.13640E-01	.30114E-01	.30114E-01	.30114E-01
.20480E-01	.30114E-01	.30114E-01	.27370E-01	.30114E-01	.30114E-01	.34460E-01	.30114E-01	.30114E-01	.30114E-01
.42120E-01	.30114E-01	.30114E-01	.51190E-01	.30114E-01	.30114E-01	.63230E-01	.30114E-01	.30114E-01	.30114E-01
.80520E-01	.30114E-01	.30114E-01	.10580E+00	.30114E-01	.30114E-01	.14120E+00	.30114E-01	.30114E-01	.30114E-01
.17660E+00	.30114E-01	.30114E-01	.21200E+00	.30114E-01	.30114E-01	.24740E+00	.30114E-01	.30114E-01	.30114E-01
.28280E+00	.30114E-01	.30114E-01	.31820E+00	.30114E-01	.30114E-01	.35360E+00	.30114E-01	.30114E-01	.30114E-01
.38900E+00	.30114E-01	.30114E-01	.42440E+00	.30114E-01	.30114E-01	.45980E+00	.30114E-01	.30114E-01	.30114E-01
.49520E+00	.30114E-01	.30114E-01	.53060E+00	.30114E-01	.30114E-01	.56600E+00	.30114E-01	.30114E-01	.30114E-01
.60140E+00	.30114E-01	.30114E-01	.63680E+00	.30114E-01	.30114E-01	.67220E+00	.30114E-01	.30114E-01	.30114E-01
.70760E+00	.30114E-01	.30114E-01	.74300E+00	.30114E-01	.30114E-01	.77840E+00	.30114E-01	.30114E-01	.30114E-01

ITER NO., IYLOCJ, IYLOCK, YERRMX, IZLOCJ, IZLOCK, ZERRMX \* 100 15 10 .166944E-04 10 15 .166981E-04

\*\*\* CONVERGED SOLUTION \*\*\*  
 CORNER FLOW WITH FILLET  
 COORDINATE SYSTEM. SIZE=30X23X23

JMAX = 23 KMAX = 23  
 MAX ITERATIONS PERFORMED = 119  
 MAX Y-ERROR = .998592E-05 AT LOC. J,K = 15, 10  
 MAX Z-ERROR = .999905E-05 AT LOC. J,K = 10, 15

J = 1 (Y-Z ARRAY)

.30114E-01	.30114E-01	.26723E-01	.33673E-01	.22417E-01	.38732E-01	.16805E-01	.46487E-01	.10370E-01	.57820E-01
.41333E-02	.73335E-01	.43390E-03	.93379E-01	0.	.11807E+00	0.	.14734E+00	0.	.18092E+00
0.	.21842E+00	0.	.25933E+00	0.	.30303E+00	0.	.34886E+00	0.	.39610E+00
0.	.44405E+00	0.	.49200E+00	0.	.53930E+00	0.	.58538E+00	0.	.62974E+00
0.	.67204E+00	0.	.71209E+00	0.	.75000E+00				

J = 2 (Y-Z ARRAY)

.33673E-01	.26723E-01	.31704E-01	.31704E-01	.27768E-01	.37626E-01	.21875E-01	.45759E-01	.14938E-01	.57216E-01
.83075E-02	.72769E-01	.42700E-02	.92804E-01	.36047E-02	.11748E+00	.35684E-02	.14678E+00	.35638E-02	.18043E+00
.35621E-02	.21800E+00	.35614E-02	.25897E+00	.35609E-02	.30273E+00	.35607E-02	.34861E+00	.35605E-02	.39590E+00
.35604E-02	.44389E+00	.35604E-02	.49187E+00	.35603E-02	.53920E+00	.35603E-02	.58531E+00	.35603E-02	.62969E+00
.35603E-02	.67201E+00	.35603E-02	.71208E+00	.35603E-02	.75000E+00				

J = 3 (Y-Z ARRAY)

.38732E-01	.22417E-01	.37626E-01	.27768E-01	.34772E-01	.34772E-01	.29284E-01	.43977E-01	.21831E-01	.56048E-01
.14476E-01	.71835E-01	.93447E-02	.91930E-01	.87795E-02	.11662E+00	.86566E-02	.14599E+00	.86361E-02	.17973E+00
.86290E-02	.21740E+00	.86257E-02	.25846E+00	.86239E-02	.30230E+00	.86228E-02	.34826E+00	.86222E-02	.39561E+00
.86215E-02	.44365E+00	.86215E-02	.49169E+00	.86214E-02	.53906E+00	.86213E-02	.58521E+00	.86212E-02	.62962E+00
.86212E-02	.67197E+00	.86212E-02	.71206E+00	.86212E-02	.75000E+00				

J = 4 (Y-Z ARRAY)

.46487E-01	.16805E-01	.45759E-01	.21875E-01	.43977E-01	.29283E-01	.39775E-01	.39775E-01	.32741E-01	.53227E-01
.24677E-01	.69891E-01	.18904E-01	.90370E-01	.16950E-01	.11523E+00	.16547E-01	.14474E+00	.16454E-01	.17864E+00
.16421E-01	.21648E+00	.16406E-01	.25769E+00	.16397E-01	.30166E+00	.16393E-01	.34772E+00	.16390E-01	.39517E+00
.16388E-01	.44330E+00	.16387E-01	.49141E+00	.16386E-01	.53885E+00	.16386E-01	.58505E+00	.16386E-01	.62952E+00
.16386E-01	.67191E+00	.16386E-01	.71203E+00	.16386E-01	.75000E+00				

J = 5 (Y-Z ARRAY)

.57820E-01	.10370E-01	.57216E-01	.14938E-01	.56048E-01	.21831E-01	.53227E-01	.32741E-01	.47634E-01	.47633E-01
.39886E-01	.65895E-01	.32980E-01	.87492E-01	.29503E-01	.11296E+00	.28369E-01	.14283E+00	.28021E-01	.17703E+00
.27891E-01	.21511E+00	.27631E-01	.25655E+00	.27799E-01	.30071E+00	.27781E-01	.34694E+00	.27770E-01	.39453E+00
.27763E-01	.44279E+00	.27759E-01	.49101E+00	.27756E-01	.53855E+00	.27755E-01	.58483E+00	.27754E-01	.62937E+00
.27753E-01	.67182E+00	.27753E-01	.71199E+00	.27753E-01	.75000E+00				

J = 6 (Y-Z ARRAY)

.73335E-01	.41333E-02	.72769E-01	.83075E-02	.71835E-01	.14476E-01	.69892E-01	.24676E-01	.65895E-01	.39886E-01
.59499E-01	.59498E-01	.52458E-01	.82704E-01	.47504E-01	.10942E+00	.45139E-01	.14005E+00	.44180E-01	.17475E+00

.43793E-01	.21322E+00	.43605E-01	.25498E+00	.43506E-01	.29941E+00	.43450E-01	.34588E+00	.43416E-01	.39367E+00
.43395E-01	.44210E+00	.43382E-01	.49047E+00	.43374E-01	.53814E+00	.43370E-01	.58453E+00	.43367E-01	.62917E+00
.43365E-01	.67169E+00	.43365E-01	.71193E+00	.43365E-01	.75000E+00				
J = 7 (Y-Z ARRAY)									
.93379E-01	.43390E-03	.92804E-01	.42700E-02	.91930E-01	.98447E-02	.90371E-01	.18904E-01	.87493E-01	.32980E-01
.82704E-01	.52457E-01	.76576E-01	.76575E-01	.71043E-01	.10458E+00	.67461E-01	.13629E+00	.65596E-01	.17175E+00
.64688E-01	.21077E+00	.64230E-01	.25296E+00	.63982E-01	.29775E+00	.63839E-01	.34452E+00	.63754E-01	.39257E+00
.63702E-01	.44122E+00	.63669E-01	.48979E+00	.63649E-01	.53762E+00	.63637E-01	.58416E+00	.63629E-01	.62891E+00
.63625E-01	.67154E+00	.63624E-01	.71186E+00	.63624E-01	.75000E+00				
J = 8 (Y-Z ARRAY)									
.11807E+00	0.	.11748E+00	.36047E-02	.11662E+00	.87795E-02	.11523E+00	.16950E-01	.11296E+00	.29503E-01
.10942E+00	.47504E-01	.10458E+00	.71042E-01	.99421E-01	.99419E-01	.95219E-01	.13193E+00	.92472E-01	.16816E+00
.90863E-01	.20783E+00	.89994E-01	.25053E+00	.89488E-01	.29575E+00	.89190E-01	.34288E+00	.89009E-01	.39124E+00
.88897E-01	.44017E+00	.88827E-01	.48896E+00	.88783E-01	.53700E+00	.88757E-01	.58371E+00	.88741E-01	.62861E+00
.88732E-01	.67136E+00	.88729E-01	.71178E+00	.88729E-01	.75000E+00				
J = 9 (Y-Z ARRAY)									
.14734E+00	0.	.14678E+00	.35684E-02	.14599E+00	.86566E-02	.14474E+00	.16547E-01	.14283E+00	.28369E-01
.14005E+00	.45138E-01	.13629E+00	.67460E-01	.13193E+00	.95218E-01	.12778E+00	.12777E+00	.12452E+00	.16443E+00
.12231E+00	.20462E+00	.12092E+00	.24783E+00	.12006E+00	.29350E+00	.11954E+00	.34102E+00	.11921E+00	.38973E+00
.11900E+00	.43896E+00	.11887E+00	.48802E+00	.11879E+00	.53629E+00	.11874E+00	.58319E+00	.11871E+00	.62826E+00
.11869E+00	.67115E+00	.11869E+00	.71166E+00	.11869E+00	.75000E+00				
J = 10 (Y-Z ARRAY)									
.18092E+00	0.	.18043E+00	.35638E-02	.17973E+00	.86361E-02	.17864E+00	.16454E-01	.17703E+00	.28021E-01
.17475E+00	.44189E-01	.17175E+00	.65595E-01	.16816E+00	.92471E-01	.16443E+00	.12452E+00	.16111E+00	.16111E+00
.15853E+00	.20152E+00	.15671E+00	.24508E+00	.15549E+00	.29114E+00	.15469E+00	.33904E+00	.15418E+00	.38811E+00
.15384E+00	.43766E+00	.15363E+00	.48701E+00	.15349E+00	.53552E+00	.15341E+00	.58264E+00	.15336E+00	.62788E+00
.15333E+00	.67092E+00	.15332E+00	.71158E+00	.15332E+00	.75000E+00				
J = 11 (Y-Z ARRAY)									
.21842E+00	0.	.21800E+00	.35621E-02	.21740E+00	.86290E-02	.21648E+00	.16421E-01	.21511E+00	.27891E-01
.21323E+00	.43792E-01	.21078E+00	.64687E-01	.20783E+00	.90882E-01	.20462E+00	.12231E+00	.20152E+00	.15853E+00
.19886E+00	.19686E+00	.19679E+00	.24255E+00	.19528E+00	.28887E+00	.19424E+00	.33709E+00	.19353E+00	.38647E+00
.19306E+00	.43633E+00	.19275E+00	.48596E+00	.19255E+00	.53472E+00	.19242E+00	.58206E+00	.19234E+00	.62749E+00
.19230E+00	.67068E+00	.19228E+00	.71147E+00	.19228E+00	.75000E+00				
J = 12 (Y-Z ARRAY)									
.25933E+00	0.	.25897E+00	.35614E-02	.25846E+00	.86257E-02	.25769E+00	.16406E-01	.25655E+00	.27831E-01
.25498E+00	.43605E-01	.25296E+00	.64229E-01	.25053E+00	.89993E-01	.24783E+00	.12092E+00	.24508E+00	.15670E+00
.24256E+00	.19679E+00	.24044E+00	.24043E+00	.23878E+00	.28686E+00	.23756E+00	.33528E+00	.23670E+00	.38492E+00
.23610E+00	.43505E+00	.23570E+00	.48494E+00	.23543E+00	.53394E+00	.23526E+00	.58149E+00	.23516E+00	.62710E+00
.23510E+00	.67045E+00	.23507E+00	.71137E+00	.23507E+00	.75000E+00				
J = 13 (Y-Z ARRAY)									
.30303E+00	0.	.30273E+00	.35609E-02	.30230E+00	.86239E-02	.30166E+00	.16397E-01	.30071E+00	.27799E-01
.29941E+00	.43506E-01	.29775E+00	.63981E-01	.29575E+00	.89488E-01	.29350E+00	.12006E+00	.29114E+00	.15448E+00

.28887E+00	.19528E+00	.28686E+00	.23878E+00	.28520E+00	.28520E+00	.28391E+00	.33373E+00	.28296E+00	.38355E+00
.28227E+00	.43389E+00	.28180E+00	.48400E+00	.28148E+00	.53322E+00	.28127E+00	.58096E+00	.28114E+00	.62674E+00
.28107E+00	.67023E+00	.28104E+00	.71127E+00	.28104E+00	.75000E+00				
J = 14	(Y-Z ARRAY)								
.34886E+00	0.	.34861E+00	.35607E-02	.34826E+00	.86228E-02	.34772E+00	.16393E-01	.34694E+00	.27781E-01
.34588E+00	.43450E-01	.34452E+00	.63839E-01	.34288E+00	.89190E-01	.34102E+00	.11954E+00	.33905E+00	.15469E+00
.33709E+00	.19424E+00	.33526E+00	.23756E+00	.33373E+00	.28391E+00	.33247E+00	.33247E+00	.33150E+00	.38240E+00
.33079E+00	.43289E+00	.33028E+00	.48318E+00	.32993E+00	.53258E+00	.32970E+00	.58049E+00	.32955E+00	.62642E+00
.32947E+00	.67003E+00	.32944E+00	.71118E+00	.32944E+00	.75000E+00				
J = 15	(Y-Z ARRAY)								
.39610E+00	0.	.39590E+00	.35605E-02	.39561E+00	.86222E-02	.39517E+00	.16390E-01	.39453E+00	.27770E-01
.39367E+00	.43416E-01	.39257E+00	.63754E-01	.39125E+00	.89009E-01	.38974E+00	.11921E+00	.38811E+00	.15417E+00
.38648E+00	.19353E+00	.38493E+00	.23669E+00	.38355E+00	.28295E+00	.38240E+00	.33150E+00	.38149E+00	.38149E+00
.38080E+00	.43208E+00	.38029E+00	.48250E+00	.37994E+00	.53204E+00	.37970E+00	.58009E+00	.37955E+00	.62614E+00
.37946E+00	.66987E+00	.37943E+00	.71110E+00	.37943E+00	.75000E+00				
J = 16	(Y-Z ARRAY)								
.44405E+00	0.	.44389E+00	.35604E-02	.44365E+00	.86218E-02	.44330E+00	.16388E-01	.44279E+00	.27763E-01
.44210E+00	.43395E-01	.44122E+00	.63702E-01	.44017E+00	.88897E-01	.43896E+00	.11900E+00	.43766E+00	.15384E+00
.43633E+00	.19306E+00	.43505E+00	.23610E+00	.43389E+00	.28227E+00	.43289E+00	.33079E+00	.43208E+00	.38079E+00
.43146E+00	.43146E+00	.43099E+00	.48197E+00	.43066E+00	.53161E+00	.43043E+00	.57977E+00	.43029E+00	.62592E+00
.43021E+00	.66973E+00	.43017E+00	.71104E+00	.43017E+00	.75000E+00				
J = 17	(Y-Z ARRAY)								
.49200E+00	0.	.49187E+00	.35604E-02	.49169E+00	.86215E-02	.49141E+00	.16387E-01	.49101E+00	.27759E-01
.49047E+00	.43382E-01	.48978E+00	.63669E-01	.48896E+00	.88827E-01	.48802E+00	.11887E+00	.48701E+00	.15363E+00
.48596E+00	.19275E+00	.48494E+00	.23570E+00	.48400E+00	.28180E+00	.48318E+00	.33028E+00	.48251E+00	.38029E+00
.48197E+00	.43099E+00	.48157E+00	.48157E+00	.48128E+00	.53129E+00	.48108E+00	.57952E+00	.48095E+00	.62575E+00
.48087E+00	.66962E+00	.48084E+00	.71099E+00	.48084E+00	.75000E+00				
J = 18	(Y-Z ARRAY)								
.53930E+00	0.	.53920E+00	.35603E-02	.53906E+00	.86214E-02	.53885E+00	.16386E-01	.53855E+00	.27756E-01
.53814E+00	.43374E-01	.53762E+00	.63649E-01	.53700E+00	.88783E-01	.53629E+00	.11879E+00	.53552E+00	.15349E+00
.53473E+00	.19255E+00	.53394E+00	.23543E+00	.53322E+00	.28148E+00	.53258E+00	.32993E+00	.53204E+00	.37994E+00
.53162E+00	.43066E+00	.53129E+00	.48128E+00	.53105E+00	.53105E+00	.53089E+00	.57934E+00	.53078E+00	.62562E+00
.53072E+00	.66955E+00	.53069E+00	.71095E+00	.53069E+00	.75000E+00				
J = 19	(Y-Z ARRAY)								
.58538E+00	0.	.58531E+00	.35603E-02	.58520E+00	.86213E-02	.58505E+00	.16386E-01	.58483E+00	.27755E-01
.58453E+00	.43370E-01	.58416E+00	.63636E-01	.58371E+00	.88756E-01	.58319E+00	.11874E+00	.58264E+00	.15341E+00
.58206E+00	.19242E+00	.58149E+00	.23526E+00	.58096E+00	.28127E+00	.58049E+00	.32970E+00	.58009E+00	.37970E+00
.57977E+00	.43043E+00	.57952E+00	.48108E+00	.57934E+00	.53088E+00	.57921E+00	.57921E+00	.57913E+00	.62553E+00
.57906E+00	.66949E+00	.57906E+00	.71093E+00	.57906E+00	.75000E+00				
J = 20	(Y-Z ARRAY)								
.62974E+00	0.	.62969E+00	.35603E-02	.62962E+00	.86212E-02	.62952E+00	.16386E-01	.62937E+00	.27754E-01
.62917E+00	.43367E-01	.62891E+00	.63629E-01	.62861E+00	.88741E-01	.62826E+00	.11871E+00	.62788E+00	.15336E+00



.62749E+00	.19234E+00	.62710E+00	.23515E+00	.62674E+00	.28114E+00	.62642E+00	.32955E+00	.62614E+00	.37955E+00
.62592E+00	.43029E+00	.62575E+00	.48095E+00	.62562E+00	.53078E+00	.62553E+00	.57913E+00	.62547E+00	.62547E+00
.62544E+00	.66945E+00	.62542E+00	.71091E+00	.62542E+00	.75000E+00				

J = 21 (Y-Z ARRAY)

.67204E+00	0.	.67201E+00	.35603E-02	.67197E+00	.86212E-02	.67191E+00	.16386E-01	.67182E+00	.27753E-01
.67169E+00	.43365E-01	.67154E+00	.63625E-01	.67136E+00	.88732E-01	.67115E+00	.11869E+00	.67092E+00	.15333E+00
.67068E+00	.19230E+00	.67045E+00	.23510E+00	.67023E+00	.28107E+00	.67003E+00	.32947E+00	.66987E+00	.37946E+00
.66973E+00	.43021E+00	.66962E+00	.48087E+00	.66955E+00	.53072E+00	.66949E+00	.57908E+00	.66945E+00	.62544E+00
.66943E+00	.66943E+00	.66942E+00	.71090E+00	.66942E+00	.75000E+00				

J = 22 (Y-Z ARRAY)

.71209E+00	0.	.71208E+00	.35603E-02	.71206E+00	.86212E-02	.71203E+00	.16386E-01	.71199E+00	.27753E-01
.71193E+00	.43365E-01	.71186E+00	.63624E-01	.71178E+00	.88729E-01	.71168E+00	.11869E+00	.71158E+00	.15332E+00
.71147E+00	.19228E+00	.71137E+00	.23507E+00	.71127E+00	.28104E+00	.71118E+00	.32943E+00	.71110E+00	.37943E+00
.71104E+00	.43017E+00	.71099E+00	.48084E+00	.71095E+00	.53069E+00	.71093E+00	.57906E+00	.71091E+00	.62542E+00
.71090E+00	.66942E+00	.71090E+00	.71090E+00	.71090E+00	.75000E+00				

J = 23 (Y-Z ARRAY)

.75000E+00	0.	.75000E+00	.35603E-02	.75000E+00	.86212E-02	.75000E+00	.16386E-01	.75000E+00	.27753E-01
.75000E+00	.43365E-01	.75000E+00	.63624E-01	.75000E+00	.88729E-01	.75000E+00	.11869E+00	.75000E+00	.15332E+00
.75000E+00	.19228E+00	.75000E+00	.23507E+00	.75000E+00	.28104E+00	.75000E+00	.32943E+00	.75000E+00	.37943E+00
.75000E+00	.43017E+00	.75000E+00	.48084E+00	.75000E+00	.53069E+00	.75000E+00	.57906E+00	.75000E+00	.62542E+00
.75000E+00	.66942E+00	.75000E+00	.71090E+00	.75000E+00	.75000E+00				

J=1,K=1,X=1,IMAX (X,Y,Z ARRAY)


0.	.30114E-01	.30114E-01	.68190E-02	.30114E-01	.30114E-01	.13640E-01	.30114E-01	.30114E-01
.20480E-01	.30114E-01	.30114E-01	.27370E-01	.30114E-01	.30114E-01	.34460E-01	.30114E-01	.30114E-01
.42120E-01	.30114E-01	.30114E-01	.51190E-01	.30114E-01	.30114E-01	.63230E-01	.30114E-01	.30114E-01
.80520E-01	.30114E-01	.30114E-01	.10580E+00	.30114E-01	.30114E-01	.14120E+00	.30114E-01	.30114E-01
.17650E+00	.30114E-01	.30114E-01	.21200E+00	.30114E-01	.30114E-01	.24740E+00	.30114E-01	.30114E-01
.28230E+00	.30114E-01	.30114E-01	.31820E+00	.30114E-01	.30114E-01	.35360E+00	.30114E-01	.30114E-01
.38900E+00	.30114E-01	.30114E-01	.42440E+00	.30114E-01	.30114E-01	.45980E+00	.30114E-01	.30114E-01
.49520E+00	.30114E-01	.30114E-01	.53060E+00	.30114E-01	.30114E-01	.56600E+00	.30114E-01	.30114E-01
.60140E+00	.30114E-01	.30114E-01	.63680E+00	.30114E-01	.30114E-01	.67220E+00	.30114E-01	.30114E-01
.70760E+00	.30114E-01	.30114E-01	.74300E+00	.30114E-01	.30114E-01	.77840E+00	.30114E-01	.30114E-01

THE PLOT CONTROL CARD IMAGE IS,


PLOT.VARIAN

FRAME	X0	Y0	XM	YM	CAL. POS
1	0.	0.	1.000000E+00	1.000000E+00	0.
2	0.	0.	1.000000E+00	1.000000E+00	0.
3	0.	0.	1.000000E+00	1.000000E+00	0.
4	0.	0.	1.000000E+00	1.000000E+00	0.

CORNER FLOW WITH FILLET  
COORDINATE SYSTEM. SIZE 30X23X23  
--- INITIAL GUESS ---  
JMAX 23 KMAX 23



CORNER FLOW WITH FILLET  
COORDINATE SYSTEM. SIZE 30X23X23  
--- CONVERGED SOLUTION ---  
JMAX 23 KMAX 23



### III. Programmer/Analyst Section

The program is written such that the array size in  $\xi$ ,  $\eta$ ,  $\zeta$  direction can be varied from problem to problem by the use of test editor on CDC 6600 machine. The array sizes are coded to be IMXLL, JMXLL, KMXLL in  $\xi$ ,  $\eta$  and  $\zeta$  direction respectively. These are changed to the appropriate numeric number by the test editor prior to compiling the program for execution. The job control cards, input explanation and other helpful hints are provided towards the beginning of main program COORDC. The program is extensively commented. Though the computer code is not structured in the true sense, extreme care was taken to avoid branching back in the code unless absolutely necessary. A brief discussion of each subroutine and their function follow.

#### A. Main Program COORDC

This program performs the following function,

- i) Initialize variables to 0.0.
- ii) Read in input data. If the field size is greater than the maximum field size allowed then the program aborts with a diagnostic message. The maximum field size allowed is ILIMIT, JLIMIT, KLIMIT and the field size input is IMAX, JMAX, KMAX. ILIMIT, JLIMIT, and KLIMIT are set to numerical value by the text editor. The storage requirement in N-S code require that IMAX, JMAX, KMAX be equal to ILIMIT, JLIMIT, KLIMIT respectively.
- iii) Specify initial guess.
- iv) Check to see if initial guess is to be printed, plotted or not. If so, then the appropriate subroutines are called.
- v) Compute attraction parameter Q and R.

- vi) Start computing solution. Do loop for maximum iterations (ITERMX) is set. For each iteration subroutine CALCOR is called. CALCOR computes solution for each iteration and also passes back maximum error and its location.
- vii) Print maximum error and partially converged solution every 50 iterations. Partially converged solution is printed only if the flag to print the initial guess is set.
- viii) Check maximum error in y and z for convergence. If convergence is reached, then an exit from the DO loop is taken.
- ix) After ITERMX iterations or convergence, which ever comes first, some more print/plot and storing of data is done.
- x) Check to see if partially or converged solution is to be printed/plotted.
- xi) If convergence has occurred, then store solution on unit 1. If convergence has not occurred, then the maximum errors in y and z computation at the last iteration and their location are printed out.

#### B. Subroutine CALCOR

This subroutine advances the solution 1 iteration. The maximum errors and their location are computed and passed back to the calling program COORDC through the argument list. The argument list is,

YERRMX -	maximum error in y
ZERRMX -	maximum error in z
IYLOCJ -	maximum y-error J location
IYLOCK -	maximum y-error K location
IZLOCJ -	maximum z-error J location
IZLOCK -	maximum z-error K location

C. Subroutine IPRTC

This subroutine is used to print initial guess, partially converged or converged solution. The argument list is,

ISOLN = 1 indicates initial guess  
= 2 indicates partially or fully converged solution  
KKK = applicable only if ISOLN = 2  
= 0 indicates partially converged solution  
= 1 indicates fully converged solution.


YERRMX, ZERRMX, IYLOCJ, IYLOCK, IZLOCJ, IZLOCK = same as in  
CALCOR.

D. Subroutine IPLTC


This subroutine is used to plot initial guess, partially converged solution or converged solution. The argument list is same as IPRTC.


E. Block Diagram

A Block Diagram is presented on the next page.









1. Report No. NASA CR-159279		2. Government Accession No.		3. Recipient's Catalog No.	
4. Title and Subtitle  Documentation of Program COORDC to Generate Coordinate System for 3-D Corners with or Without Fillet Using Body-Fitted Curvilinear Coordinates				5. Report Date June 1980	
				6. Performing Organization Code	
7. Author(s) Dilip Kumar				8. Performing Organization Report No. R-SAL-06/80-03	
9. Performing Organization Name and Address Systems & Applied Sciences Corp. 17 Research Drive Hampton, VA 23666				10. Work Unit No.	
				11. Contract or Grant No. NAS1-15604	
12. Sponsoring Agency Name and Address National Aeronautics & Space Administration Washington, DC 20546				13. Type of Report and Period Covered Contractor Report	
				14. Sponsoring Agency Code	
15. Supplementary Notes  Technical Monitor - Dr. Julius Harris, NASA Langley Research Center					
16. Abstract  The computer program COORDC generates a body-fitted curvilinear coordinate system for corner geometry with or without corner fillets. It is assumed that at any given $\xi$ , $x$ remains constant; consequently the only variation is in $y$ and $z$ . It is also assumed that for all $\xi$ 's in the physical plane the coordinate system in $y$ - $z$ plane is similar. This enables solution of coordinate system for one particular $\xi = 1$ ( $x$ for $\xi = 1$ is arbitrarily chosen to be 0.0) and the solution for all other $\xi$ plane can be easily specified once the coordinates in the physical plane on the line $1 \leq \xi \leq IMAX$ , $\eta = 1$ , $\zeta = 1$ are specified.					
17. Key Words (Suggested by Author(s)) Navier Stokes, compressible three dimensional, curvilinear coordinate systems, corner fillets, COORDC			18. Distribution Statement  <del>RESTRICTED</del> DISTRIBUTION		
19. Security Classif. (of this report) Unclassified	20. Security Classif. (of this page) Unclassified	21. No. of Pages 57	22. Price*		

**End of Document**